


EasyView



MT-200D, MT-250D Installation Instruction

1.0 Installation and Startup Guide

Install Environment

Where Used

The MT-200 Series is designed for use in a factory environment. It is designed to operate from 32 to 113 °F (0 to 45 °C) temperatures, as found in most industrial environments. It may not be suitable for use in certain outdoor applications. Please consult the factory for advised usage in outdoor applications.

NEMA Rating

The MT-200 Series front bezel is NEMA 4 rated. When installed properly in a NEMA 4 panel, the NEMA 4 rating of the panel will not be compromised. This means that fluids will not enter the panel during wash downs.

Electrical Environment

The MT-200 Series has been tested to conform to European CE requirements. This means that the circuitry is designed to resist the effects of electrical noise. This does not guarantee noise immunity in severe cases. Proper wire routing and grounding will insure proper operation.

Mechanical Environment

Avoid installing units in environments where severe mechanical vibration or shocks are present.



2.0 Installation Instructions

2.1 Mounting Instructions

2.1.1 Location Considerations

Care should be taken when locating equipment behind the unit to ensure that AC power wiring, PLC output modules, contactors, starters and relays, and any other source of electrical interference are located away from the back of the unit.

Particular note should be taken to the position of variable speed drives and switching power supplies. Their input and load cables should be screened to a central star earth point.

2.1.2 Making a NEMA-4 Mounting

Panel Details

The unit can be mounted into panels with a depth of 4”(105mm). It is recommended that the unit be mounted on the front panel of a steel enclosure, through an appropriate opening*. Allow a clearance of 1”(25mm) around the sides of the unit for mounting hardware. Allow clearance for cable connections to the back of the unit. Unit depth may vary according to cable type used. Typically, plan a depth to accommodate at least 4”(105mm) behind the panel.

NEMA-4 Mounting

Put the unit through the panel cut out. Slide the clamps into the 6 holes provided around the case. Tighten the clamping screws in an even pattern until the unit is secured in the panel.

Caution!

Do not over tighten mounting clamps!

Note:

Specifications

Note: To seal to NEMA-4 specifications, all supplied mounting clamps must be used and panel cannot flex more than 0.010”.

2.1.3 Environmental Considerations



- The MT-200 are to be used indoors as built in displays. Make sure that the displays are installed correctly and that the operating limits are followed (See Specifications).
- Do not operate the unit in areas subject to explosion hazards due to flammable gases, vapors or dusts.
- The unit should not be installed where fast temperature variations and/or high humidity are present. This will cause condensation of water in the device.
- Do not install these terminals in environments where have inflammable gases.

2.2 Power Connections

Make sure that all local and national electrical standards are met when the installing the unit. Contact your local authorities to determine which codes apply.

2.2.1 Power Requirements



Power

The MT-200 can be powered by DC power only. The specified voltage range is 24Volts DC +/- 5%. This insures compatibility with most controller DC systems.

The power conditioning circuitry inside the unit is accomplished by a switching power supply. The peak starting current can be as high as 700mA.



Fusing Requirements

If the display does not come on within 2 seconds of power up, remove power. An internal fuse will prevent damage if the polarity of the DC power is incorrect. Check wiring to insure proper connections and try to power up again.



Caution High Voltage

An Internal fuse will prevent damage for over voltage condition however it isn't guaranteed.

DC voltage sources should provide proper isolation from main AC power and similar hazards.



Caution Emergency Stop

A Hard-wired EMERGENCY STOP should be fitted in any system using an MT-200 to comply with ICS Safety Recommendations.



**Caution
Supply Voltage
Condition**

Do not power the MT-200 and inductive DC loads, or input circuitry to the controller, with the same power supply. Note: The 24 VDC output from some controllers may not have enough current to power the MT-200.



**Caution
Wire Routing**

Wire lengths should be minimized (Maximum 1600' (500 m) shielded, 1000' (300 m) unshielded).

Wires should be run in pairs with a neutral or common paired with a hot or signal line.

If wiring is to be exposed to lightning or surges, use appropriate surge suppression devices.

Keep AC, high energy, and rapidly switching DC wiring separate from signal wires.

Equip ungrounded DC supplies with a resistor and capacitor in parallel to earth ground. This provides a path for static and high frequency dissipation. Typical values to use are 1M Ω and 4700pF.

Connection

To make a connection, strip about 3/8" of insulation off the end of the wire, turn the connector screw counterclockwise until the gap is wide open, insert the wire all the way in, and turn the screw clockwise until it's tight.

Connect positive DC line to the '+24V' terminal and the DC ground to the '0V' terminal.

2.2.2 Grounding Requirements



Chassis ground must be used. DC ground is not directly coupled to Earth ground internally. It is preferable not to ground DC negative return to chassis ground as poor site earths can introduce noise into a system, but if necessary an earth connection should be made, from the power supply return point to the central star earth point. Ground conductors should be as short and as large in size as possible. The conductors must always be large enough to carry the maximum short circuit current of the path being considered. Ground conductors should be connected to a tree from a central star earth ground point. This ensures that no ground conductor carries current from any other branch.

2.2.3 CE Requirements

To make an MT-200 comply with EMC directives, and to reduce susceptibility to electrical interference, a separate #14 AWG ground wire should be taken to the chassis ground terminal of the power connector. This ground connection should be run directly to the central star earth connection point (as recommended in most Installation Instructions).

2.2.4 Safety Guidelines

This section presents recommended installation practices, and procedures. Since no two applications are identical, these recommendations should be considered as guidelines.

**Hardware
Considerations**

WARNING!



The system designer should be aware that devices in Controller systems could fail and thereby create an unsafe condition. Furthermore, electrical interference in an operator interface, such as an MT-200, can lead to equipment start-up, which could result in property damage and/or physical injury to the equipment operator.

If you, or your company, use any programmable control systems that require an operator or attendant, you should be aware that this potential safety hazard exists and take appropriate precautions. Although the specific design steps depend on your particular application, the following precautions generally apply to installation of solid-state programmable control devices. In addition, these precautions conform to the guidelines for installation of Controllers as recommended in the NEMA ICS 3-304 Control Standards.

Programming Considerations

To conform with ICS Safety Recommendations, checks should be placed in the controller to ensure that all writable registers that control critical parts of plant or machinery have limit checks built into the program, with an out-of-limit safe shut down procedure to ensure safety of personnel.

ICS 3-304.81 Safety Recommendations:

Consideration should be given to the use of an emergency stop function, which is independent of the programmable controller.

Where the operator is exposed to the machinery, such as in loading or unloading a machine tool, or where the machine cycles automatically, consideration should be given to the use of an electromechanical override or other redundant means, independent of the programmable controller, for starting and interrupting the cycle.

If provision is required for changing programs while the equipment is in operation, consideration should be given to the use of locks or other means of assuring that only authorized personnel can make such changes.

*These recommendations are intended as safeguards against the failure of critical components and the effects of such failures or the inadvertent errors that might be introduced if programs are changed while the equipment is in operation. **

- The ICS 3-304.81 Safety Recommendations are reproduced by permission of the National Electrical Manufacturers Association from NEMA ICS 3-304

2.3 Communications Connections

The ports as you look at the back of the case, are the ports for connecting to a printer, PLC or some external device (Controller Connectors).

2.3.1 RS-232 PORT

Cable Requirements

Different cables are required for various devices.

Caution


Restrict cable length to less than 500' (150m) for RS485/422 devices and 50' (15m) for RS232 devices to avoid communications problems. Communications problems cause the display to show "PLC no response..." until communications can be established. The COM light on the front of the MT-200 will turn on with each communication.

Shielded cable must be used for long lengths or cables run in an electrically noisy environment.

Do not run cables next to AC power lines or near sources of electrical noise.

Be sure that the cable ends have been inserted all of the way into mating connectors and are secure

Pin Designations




RS-232

Pin assignment of the 9 Pin, Female, SUB-D, RS-232 Port. This port is used for connecting the MT-200 to a controller and Computer.

Pin#	Symbol	Function
1	Not used	
2	TxD	Transmitted Data
3	RxD	Received Data
4	Not used	
5	GND	Signal Ground
6	Not used	
7	CTS	Clear to send input
8	RTS	Ready to send output
9	Not used	

2.3.2 RS-422 PORT

Pin Designations



RS-422

Pin assignment of the 9 Pin, Female, SUB-D RS-422 Port


Pin#	Symbol	Function
1	+5V	
2	Tx+	RS485 Transmit
3	Tx-	RS485 Transmit
4	Rx+	RS485 Receive
5	Rx-	RS485 Receive
6	GND	Signal Ground
7	CTS*	Clear to send input
8	RTS*	Ready to send output
9	Not used	

*TTL level

MT-200 - RS232

PC - RS232

MT-200 to PC Cable Configuration



2.3.3 Dip Switch

The DIP Switches

1	Operation	ON	Touch	ON	Parameter	OFF		OFF	Online
2	Mode	ON	Calibration	OFF	setting	ON		OFF	operation
3	Program speed	ON	19200		OFF	9600			
4	Program/run	ON	Program		OFF	Run			

SW4: to set the operation mode of the *MT200*

ON: to load project file from the PC

OFF: to execute the function assigned by the **SW1** and **SW2**

SW3: to set the transmission speed between the PC and *MT200*

ON: to set the transmission speed as 19200 baud rate

OFF: to set the transmission speed as 9600 baud rate

[SW1, SW2]: to assign the operation mode when the switch SW4 is OFF

[ON, ON]: to calibrate the touch panel.

This operation mode is provided for a skilled person to calibrate the touch panel. To avoid the calibration data loss, please do not select this operation mode arbitrary.

[OFF, ON]: to set the system parameters of *MT200*

[OFF, OFF]: to link with the PLC. It is the online operation mode.

Note: that any change of switch settings does not go into effect until the system is reset. System is reset when power up or pressing the RESET button.

2/4 Wires setting for RS422 port

Auto setting; you don't have to change the jumper setting.

2.4 CE Requirements

EU directives that apply to the MT-200 Series:

- EMC Directive (89/336/EEC, 92/31/EEC, 93/68/EEC) electromagnetic emissions and immunity
- Machinery Directive (89/392/EEC, 91/368/EEC, 93/44/EEC, 93/68/EEC) machine safety
- MT-200 products will be CE-marked to indicate compliance with the EMC Directive.

The MT-200 Series has been designed to operate satisfactorily in electromagnetic noise (immunity) and without emitting high levels of electrical noise into the environment (emission). The units are designed to meet European Community standards when installed per the wiring instructions in this manual.

Compatibility Standards

The MT-200 has been designed to meet electromagnetic compatibility for industrial environments.

- CISPR (EN 55011) Group 1, Class A Radiated Emissions levels
- EN50081-2 Generic emission standard, industrial environment (Also US FCC Class A)
- EN50082-2 Generic immunity standard, industrial environment

3.0 Specifications

	MT-250D	MT-200D
--	----------------	----------------

Hardware Specification

Display	9.4" high contrast, blue mode LCD	5.7" high contrast, blue mode LCD
Brightness	60 cd/m2	60 cd/m2
Color	Monochrome	Monochrome
Contrast Ratio	15:1	15:1
Resolution (WxH dots)	640 x 480	320 x 240
Back light	CCFT (MTBF 15,000hr, w/ auto shutdown, replaceable)	
Touch panel	4 wires resistive type	
Touch Accuracy (cell)	80(W) x 60(H)	40(W) x 30(H)
Surface Hardness	4H	
Serial Interface	PC/PLC-HMI (RS-232) PLC –HMI (RS-485)	PC/PLC-HMI (RS-232) PLC –HMI (RS-485)
Processor	8-bit processor	8-bit processor
Flash Memory	512KB	512KB
Recipe memory	N/A	N/A
RTC	N/A	N/A
Parallel printer port	N/A	N/A
System Diagnostic	Power failure detection	

General Specification


Input Power	24 VDC +/- 5%	
CE	Complies with EN50081-2 and EN50082-2 standards	
FCC	Complies with FCC Class A	
Voltage resistance	500VAC (1 min.)	
Isolation resistance	Exceed 50MΩ at 500VDC	
Vibration endurance	10 to 25 Hz (X,Y,Z direction 2G 30minutes)	
Protection structure	IP65 front panel (O ring seal)	
Operating Temperature	0~45° C	
Operation humidity	10-90% RH (non –condense)	
Enclosure	Plastic PBT + PC	
Dimensions HxWxD	297x230x40mm	204x150x75mm
Panel cutout dimension	282 x 213 mm	192 x 138 mm
Weight	Approx. 1.8 kg	Approx. 0.9 kg

Software

Screen Editor Software	EasyBuilder 200
------------------------	-----------------

4.0 Dimensions

Dimensions of MT-250D



Dimensions of MT-200D

