Vision™PLC+HMI

V130-33-TR34/V130-J-TR34 V350-35-TR34/V350-J-TR34 V430-J-TR34 Technical Specifications

Order Information

Item

V130-33-TR34 PLC with Classic panel, Monochrome display 2.4"
V130-J-TR34 PLC with Flat panel, Monochrome display 2.4"
V350-35-TR34 PLC with Classic panel, Color touch display 3.5"
V350-J-TR34 PLC with Flat panel, Color touch display 3.5"
V430-J-TR34 PLC with Flat panel, Color touch display 4.3"

You can find additional information, such as wiring diagrams, in the product's installation guide located in the Technical Library at www.unitronics.com.

Power	Supp	y
-------	------	---

	V130-TR34	V350-TR34	V430J-TR34
Item	V130J-TR34	V350J-TR34	
Input voltage	24VDC		
Permissible range	20.4VDC to 28.8VDC with	ith less than 10% ripple	
Max. current consumption	See Note 1		
npn inputs	245mA@24VDC	265mA@24VDC	265mA@24VDC
pnp inputs	170mA@24VDC	180mA@24VDC	180mA@24VDC

Notes:

 To calculate the actual power consumption, subtract the current for each unused element from the maximum current consumption value according to the values below:

	Backlight	Ethernet card	Relay Outputs (per output)
V130/J	10mA	35mA	5mA
V350/J/V430J	20mA	35mA	5mA

Digital Inputs

Number of inputs	22. See note 2
Input type	See note 2
Galvanic isolation	None
Nominal input voltage	24VDC
Input Voltage	Normal digital in

voltage	Normal digital input	High Speed input. See Note 3
pnp (source)	0-5 VDC for Logic '0' 17-28.8 VDC for Logic '1'	0-3 VDC for Logic '0' 20.4-28.8 VDC for Logic '1'
npn (sink)	17-28.8 VDC for	20.4-28.8 VDC for Logic '0'

0-5 VDC for Logic '1' Input Current

I0-5 5.4mA@24VDC I6-21 3.7mA@24VDC

Input impedance

10-5 4.5ΚΩ16-21 6.5ΚΩ

Response Time 10ms typical, when used as normal digital input

Input Cable length

Normal digital Input Up to 100 meters

High Speed Input Up to 50 meters, shielded, see Frequency table below

11/15 Vision™PLC+HMI

High speed inputs

Specifications below apply when wired as HSC/shaft-encoder.

See Note 2.

Frequency, HSC

Driver type	pnp/npn	Push-pull
Cable length (max.)		
10m	95kHz maximum	200kHz maximum
25m	50kHz maximum	200kHz maximum
50m	25kHz maximum	200kHz maximum

Frequency, Shaft-encoder

Driver type	pnp/npn	Push-pull
Cable length (max.)		
10m	35kHz maximum	100kHz maximum
25m	18kHz maximum	100kHz maximum
50m	10kHz maximum	100kHz maximum

Duty cycle 40-60% Resolution 32-bit

Notes:

2. V130/V350/V130J/V350J/V430J-TR34 models comprise a total of 22 inputs and 8 relay, 4 npn outputs.

Input functionality can be adapted as follows:

22 inputs may be used as digital inputs. They may be wired, in a group, and set to either npn or pnp via a single jumper.

In addition, according to jumper settings and appropriate wiring:

- Inputs 14 and 15 can function as either digital or analog inputs.
- Inputs 0, 2, and 4 can function as high-speed counters, as part of a shaft-encoder, or as normal digital inputs.
- Inputs 1, 3, and 5 can function as either counter reset, as part of a shaft-encoder, or as normal digital inputs.
- If inputs 0, 2 and 4 are set as high-speed counters (without reset), inputs 1, 3 and 5 can function as normal digital inputs.
- 3. If you configure an input as high-speed, you can use an end-device that comprises push-pull drive type. In this case, the high-speed input voltage ratings for npn/pnp apply.

Analog Inputs

Number of inputs 2, according to wiring as described above in Note 2

Input type Multi-range inputs: 0-10V, 0-20mA, 4-20mA

 Input range
 0-20mA, 4-20mA
 0-10VDC

 Input impedance
 243Ω
 >150KΩ

 Maximum input rating
 25mA, 6V
 15V

Galvanic isolation None

Conversion method Successive approximation

Resolution (except 4-20mA) 10-bit (1024 units)
Resolution (at 4-20mA) 204 to 1023 (820 units)

Conversion time One configured input is updated per scan. See Note 4

Precision 0.9%

Status indication Yes – if an analog input deviates above the permissible range,

its value will be 1024.

Notes:

4. For example, if 2 inputs are configured as analog, it takes 2 scans to update all analog values.

Relay Outputs

Number of outputs 8 relay (in 2 groups). See Note 5

Output type SPST-NO (Form A)

Galvanic isolation By relay

Type of relay Tyco PCN-124D3MHZ or compatible

Output current 3A maximum per output (resistive load) 8A maximum total per common

(resistive load) 8A maximum total per Rated voltage 250VAC/30VDC

Minimum load 1mA. 5VDC

Life expectancy 100k operations at maximum load

Response time 10ms (typical)

Contact protection External precautions required (see Increasing Contact Life Span in the product's

Installation Guide)

Notes:

5. Outputs 4, 5, 6, and 7 share a common signal. Outputs 8, 9, 10, and 11 share a common signal. 11/15 Vision™PLC+HMI

Transistor Outputs

Number of outputs 4 npn (sink). See Note 6 Output type N-MOSFET, (open drain)

Galvanic Isolation None

Maximum output current 100mA per output

Rated voltage 24VDC Maximum delay OFF to ON $1\mu s$ Maximum delay ON to OFF $10\mu s$

HSO freq. range with 5Hz-200kHz (at maximum load resistance of 1.5kΩ)

resistive load

(resistive load)

Maximum ON voltage drop 1VDC Short-circuit protection None

Voltage range 3.5V to 28.8VDC

Notes:

6. Outputs 0, 1, 2 and 3 share a common 0V signal.

The 0V signal of the output must be connected to the controller's 0V.

Graphic Display Scree	n		
Item	V130-TR34 V130J-TR34	V350-TR34 V350J-TR34	V430J-TR34
LCD Type	STN, LCD display	TFT, LCD display	TFT, LCD display
Illumination backlight	White LED	White LED	White LED
Display resolution	128x64 pixels	320x240 pixels	480x272 pixels
Viewing area	2.4"	3.5"	4.3"
Colors	Monochrome	65,536 (16-bit)	65,536 (16-bit)
Screen Contrast	Via software	Fixed	Fixed
	(Store value to SI 7,		
	values range: 0 to 100%)		
Touchscreen	None	Resistive, analog	Resistive, analog
'Touch' indication	None	Via buzzer	Via buzzer
Screen brightness control	Via software (Store value to SI 9, 0 = Off, 1 = On)	Via software (Store value to SI 9, values	range: 0 to 100%)
Virtual Keypad	None	Displays virtual keyboard w data entry.	hen the application requires
Keypad			
Item	V130-TR34 V130J-TR34	V350-TR34 V350J-TR34	V430J-TR34
Number of keys	20 keys,including 10 user-labeled keys	5 programmable function ke	eys
Key type	Metal dome, sealed membr	ane switch	
Slides	Slides may be installed in the operating panel faceplate to custom-label the keys. Refer to V130 Keypad Slides.pdf. A complete set of blank slides is available by separate order	Slides may be installed in the operating panel faceplate to custom-label the keys. Refer to V350 Keypad Slides.pdf. Two sets of slides are supplied with the controller: one set of arrow keys, and one blank set.	None

TR34 J-TR34 3 3 3 3 Quantity TR34 V350-1 J-TR34 V350J- V430J- 8192 4096	-TR34 -TR34 MB MI	1MB 12MB 512KB Value Bit (coil) 16-bit signed/unsigned
Quantity TR34 V350-1 J-TR34 V350J V430J 8192 4096	Symbo FR34 -TR34 -TR34 -TR34 -TR34 -TR34	12MB 512KB Value Bit (coil) 16-bit signed/unsigned
Quantity TR34 V350-1 J-TR34 V350J V430J 8192 4096	Symbo FR34 -TR34 -TR34 -TR34 -TR34 -TR34	12MB 512KB Value Bit (coil) 16-bit signed/unsigned
Quantity TR34 V350-1 J-TR34 V350J V430J 8192 4096	512KB Symbo FR34 -TR34 -TR34 MB MI	512KB Value Bit (coil) 16-bit signed/unsigned
Quantity TR34 V350-1 J-TR34 V350J V430J 8192 4096	Symbo FR34 -TR34 -TR34 MB MI	Bit (coil) 16-bit signed/unsigned
TR34 V350-1 J-TR34 V350J- V430J- 8192 4096	TR34 -TR34 -TR34 MB MI	Bit (coil) 16-bit signed/unsigned
J-TR34 V350J- V430J- 8192 4096	-TR34 -TR34 MB MI	16-bit signed/unsigned
4096	MI	16-bit signed/unsigned
		0 0
		00111111111111
512	ML	32-bit signed/unsigned
256	DW	32-bit unsigned
64	MF	32-bit signed/unsigned
1024	XB	Fast Bits (coil) - not retained
512	XI	16 bit signed/unsigned (fast, not retained)
256	XL	32 bit signed/unsigned (fast, not retained)
64	XDW	32 bit unsigned (fast, not retained)
384	Т	Res. 10 ms; max 99h, 59 min, 59.99
32	С	32-bit
	64 384	64 XDW 384 T

Removable Memory

Micro SD card Compatible with standard SD and SDHC; up to 32GB store datalogs, Alarms,

15µs per 1kb

of typical

application

192K fixed data (read-only data, ingredient names, etc) Expandable via SD card. See Removable Memory below

Trends, Data Tables, backup Ladder, HMI, and OS.

See Note 7

Up to 1024

20µs per 1kb

of typical

application

Notes:

HMI displays

Program scan time

7.User must format via Unitronics SD tools utility.

11/15 Vision™PLC+HMI

Communication Ports

Input voltage

Port 1 1 channel, RS232/RS485 and USB device (V430/V350/V350J only). See Note 8

Galvanic isolation No.

Baud rate 300 to 115200 bps

RS232

±20VDC absolute maximum

Cable length 15m maximum (50')

RS485

Input voltage -7 to +12VDC differential maximum

Cable type Shielded twisted pair, in compliance with EIA 485

Cable length 1200m maximum (4000')

Nodes Up to 32

USB device

(V430/V350/V350J only)

Port type Mini-B, See Note 10

Specification USB 2.0 complaint; full speed Cable USB 2.0 complaint; up to 3m

Port 2 (optional) See Note 9
CANbus (optional) See Note 9

Notes:

8. This model is supplied with a serial port: RS232/RS485 (Port 1). The standard is set to either RS232 or RS485 according to jumper settings. Refer to the product's Installation Guide.

- 9. The user may order and install one or both of the following modules:
 - An additional port (Port 2). Available port types: RS232/RS485 isolated/non-isolated, Ethernet
 - A CANbus port

Port module documentation is available on the Unitronics website.

 Note that physically connecting a PC to the controller via USB suspends RS232/RS485 communications via Port 1. When the PC is disconnected, RS232/RS485 resumes.

I/O Expansion

Local

Additional I/Os may be added. Configurations vary according to module.

Supports digital, high-speed, analog, weight and temperature measurement I/Os. Via I/O Expansion Port. Integrate up to 8 I/O Expansion Modules comprising up

to 128 additional I/Os. Adapter required (P.N. EX-A2X).

Remote Via CANbus port. Connect up to 60 adapters to a distance of 1000 meters from

controller; and up to 8 I/O expansion modules to each adapter (up to a total of

512 I/Os). Adapter required (P.N. EX-RC1).

Miscellaneous

Clock (RTC) Real-time clock functions (date and time)

Battery back-up 7 years typical at 25°C, battery back-up for RTC and system data, including

variable data

Battery replacement Yes. Coin-type 3V, lithium battery, CR2450

Dimension	ns			
Item		V130-TR34 V130J-TR34	V350-TR34 V350J-TR34	V430J-TR34
Size	Vxxx	109 x 114.1 x 68mm (4.29 x 4.49 x 2.67"). See Note 11	109 x 114.1 x 68mm (4.29 x 4.49 x 2.67"). See Note 11	
	Vxxx-J	109 x 114.1 x 66mm (4.92 x 4.49 x 2.59"). See Note 11	109 x 114.1 x 66mm (4.92 x 4.49 x 2.59"). See Note 11	136 x 105.1 x 61.3mm (5.35 x 4.13 x 2.41"). See Note 11
Weight		227g (8 oz)	235g (8.28 oz)	260g (9.17 oz)

Notes:

11. For exact dimensions, refer to the product's Installation Guide.

_					
En	17/11	\sim	٦m	Δr	۱.

0 to 50°C (32 to 122°F) Operational temperature -20 to 60°C (-4 to 140°F) Storage temperature Relative Humidity (RH) 10% to 95% (non-condensing) Panel mounted (IP65/66/NEMA4X) Mounting method DIN-rail mounted (IP20/NEMA1) Operating Altitude 2000m (6562 ft) Shock IEC 60068-2-27, 15G, 11ms duration Vibration IEC 60068-2-6. 5Hz to 8.4Hz. 3.5mm constant amplitude. 8.4Hz to 150Hz, 1G acceleration.

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the forgoing from the market.

All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information.

The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R"G) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.