

2024

eRetail3.2 User Manual

V1.0

DALIAN SERTAG TECHNOLOGY CO., LTD

Version History

| Version | Date | Summarize | Author | Approval |
|---------|------------|-----------|--------|----------|
| 1.0 | 2024-07-19 | | | |
| | | | | |
| | | | | |
| | | | | |



Catalog

| | | |
|-------|--------------------------------------|----|
| 1 | Summary..... | 6 |
| 1.1 | System Architecture..... | 6 |
| 1.2 | Business Architecture..... | 6 |
| 2 | System Login..... | 6 |
| 3 | System Home..... | 7 |
| 4 | Common Toolbar..... | 8 |
| 5 | Shop Management..... | 9 |
| 5.1 | Shop List..... | 9 |
| 5.1.1 | Additional Shop..... | 10 |
| 5.1.2 | Edit Shop..... | 11 |
| 5.1.3 | Find Shop..... | 11 |
| 5.1.4 | Delete Shop..... | 12 |
| 5.2 | Base Station Management..... | 12 |
| 5.2.1 | Query Base Station..... | 12 |
| 5.2.2 | Edit Base Station..... | 13 |
| 5.2.3 | Base station OTA..... | 13 |
| 5.2.4 | Delete base station..... | 14 |
| 5.2.5 | Export Base Station..... | 14 |
| 5.3 | Electronic price tag Management..... | 15 |
| 5.3.1 | Add price tag..... | 15 |
| 5.3.2 | Check price tag..... | 16 |
| 5.3.3 | Refresh price tag..... | 16 |
| 5.3.4 | Delete price tag..... | 17 |
| 5.3.5 | price tag flash..... | 17 |
| 5.3.6 | Price tag import and export..... | 18 |
| 5.3.7 | Product Binding and Unbinding..... | 19 |
| 5.3.8 | Combine Template Binding..... | 20 |
| 5.4 | Digital Signage Management..... | 21 |
| 5.4.1 | Check price tag..... | 21 |
| 5.4.2 | Import and export price tag..... | 21 |
| 5.4.3 | Product Bind and Unbind..... | 22 |
| 5.4.4 | Screen on and screen off..... | 23 |
| 5.4.5 | Synchronize device status..... | 24 |
| 5.4.6 | Refresh price tag..... | 24 |
| 5.4.7 | Delete price tag..... | 24 |
| 5.4.8 | Preview price tag..... | 25 |
| 5.5 | Area Management..... | 26 |
| 5.5.1 | Adding Area and Sub-Area..... | 26 |
| 5.5.2 | Edit area..... | 27 |
| 5.5.3 | Delete area..... | 28 |
| 5.5.4 | Bound area material..... | 28 |
| 5.6 | Advertisement screen management..... | 30 |

| | |
|---|----|
| 5.6.1 Enquiry Device | 30 |
| 5.6.2 Product Bind and Unbind | 30 |
| 5.6.3 Advertising Screen Editor | 32 |
| 5.6.4 Advertising Screen Preview | 33 |
| 5.6.5 Remote control | 34 |
| 5.6.6 Delete Device | 35 |
| 5.7 Video Service Management | 35 |
| 5.7.1 Enquiry Service | 35 |
| 5.7.2 Delete Service | 36 |
| 6 Data management..... | 36 |
| 6.1 Product Management | 36 |
| 6.1.1 Custom List | 36 |
| 6.1.2 Enquiry Product | 37 |
| 6.1.3 Add Product | 37 |
| 6.1.4 Edit Product | 38 |
| 6.1.5 Delete Product | 39 |
| 6.1.6 Product Import and Export | 40 |
| 6.1.7 Product Material Bind | 41 |
| 6.1.8 Quick Bind..... | 42 |
| 6.1.9 Import and export clip bind | 43 |
| 6.2 Plan Task..... | 45 |
| 6.2.1 Add Task..... | 45 |
| 6.2.2 Modify Task..... | 46 |
| 6.2.3 Delete Task..... | 47 |
| 6.3 Material Management | 47 |
| 6.3.1 Enquiry Material | 47 |
| 6.3.2 Upload material | 48 |
| 6.3.3 Material Classification Management | 49 |
| 6.3.4 Edit material..... | 50 |
| 6.3.5 Review Material | 50 |
| 6.3.6 Delete material | 51 |
| 6.3.7 Online material | 52 |
| 6.4 Display Management | 53 |
| 6.4.1 Check price tag..... | 53 |
| 6.4.2 Import display information..... | 54 |
| 6.4.3 Delete shelf..... | 54 |
| 7 Data query | 55 |
| 7.1 Electronic price tag communication records..... | 55 |
| 7.1.1 Enquiry Record | 55 |
| 7.1.2 Preview Price Tag | 55 |
| 7.2 Digital Signage Communication Records..... | 56 |
| 7.2.1 Enquiry record..... | 56 |
| 7.2.2 Details of communication record | 57 |
| 7.3 Data Synchronization Record | 57 |

| | |
|--|----|
| 7.4 System Log Query | 58 |
| 7.4.1 Query log | 58 |
| 7.4.2 Log details..... | 58 |
| 8 Template Management | 59 |
| 8.1 ESL Template..... | 59 |
| 8.1.1 Enquiry Template | 59 |
| 8.1.2 Add Template | 59 |
| 8.1.3 Import Template | 60 |
| 8.1.4 Edit Template | 60 |
| 8.1.5 Delete Template | 61 |
| 8.1.6 Download Template | 61 |
| 8.1.7 Online Template | 62 |
| 8.2 DSL Template | 63 |
| 8.2.1 Enquiry Template | 63 |
| 8.2.2 Add Template | 63 |
| 8.2.3 Import Template | 64 |
| 8.2.4 Edit Template | 65 |
| 8.2.5 Delete Template | 65 |
| 8.2.6 Download Template | 66 |
| 8.2.7 Online Template | 66 |
| 8.3 Template theme..... | 67 |
| 8.3.1 Query theme..... | 67 |
| 8.3.2 Add theme | 68 |
| 8.4 Holiday Management..... | 69 |
| 8.4.1 Add Holiday..... | 69 |
| 8.4.2 Delete Holiday..... | 70 |
| 9 System Management..... | 70 |
| 9.1 User Management | 70 |
| 9.1.1 Enquiry User | 70 |
| 9.1.2 Add User | 71 |
| 9.1.3 Edit user..... | 72 |
| 9.1.4 Delete user..... | 72 |
| 9.1.5 Reset Password | 73 |
| 9.2 Rights Management..... | 74 |
| 9.3 Organizational Structure | 75 |
| 9.3.1 Add Organization..... | 75 |
| 9.3.2 Edit Organization..... | 75 |
| 9.3.3 Delete Organization..... | 76 |
| 9.4 Parameter setting | 76 |
| 9.5 Administrator Tools..... | 77 |
| 9.6 System Configuration | 79 |
| 9.6.1 System parameter | 79 |
| 9.6.2 Base Station Configuration Parameter | 80 |
| 9.6.3 Message stack | 80 |

9.7 System Font Management 81

9.8 Application Management..... 82

 9.8.1 Search App 82

 9.8.2 Download App 82

 9.8.3 Publish App 83



1 Summary

1.1 System Architecture

The system B/S architecture can be divided into a database, front-end web application

The database is the data storage container that stores system and user information (this system uses MySQL as the storage database);

The front-end web application is based on the web browser client application, default port 4000;

1.2 Business Architecture

The management system deployed in the cloud server provides system administrators and business personnel with system operation status, daily operation, and data queries.

The system is divided into 7 modules: home page, my common use, shop management, data management, data query, template management, and system management.

【Home】 : System statistics, real-time information, label type distribution, traffic analysis.

【My Frequently Used】 : product management, material management, ESL templates.

【Store Management】 : Store list, base station management, electronic price tag management, digital signage management, area management, advertising screen management, video server management.

【Data Management】 : product management, planning tasks, material management, display management.


【Data Query】 : Electronic price tag communication query, digital signage communication management, data synchronization records, system log query.

【Template Management】 : ESL templates, DSL templates, template themes, holiday management;


【System Management】 : User management, permission setting, organizational structure, parameter setting, administrator tools, system configuration, system font management, application management.

2 System Login

Open the browser, enter the URL (server IP: 4000) to open the login interface, and enter the background account and password (initial administrator account: admin, password: Pass99), it is recommended that the first time you log in the shortcut will be sent to the desktop.



3 System Home



【System Statistics】: Displays the basic overview of shops, base stations, electronic price tags, digital signage, and commodities within the price tag system;

【Real-time information】: Display the distribution of the number of each online status of the current system base station, ESL, DSL, including online, offline, and work in progress status;


【Label Type Distribution】: Statistical chart showing the proportion of the total number of electronic price tags that have been deployed recently.

【Traffic Analysis】: Displays the input and output data traffic of the system by time;

4 Common Toolbar


1. My common use

You can quickly access the three modules that are frequently used by users.




2. Change of shops

You can switch the shop you want to view in the upper right corner, after switching, only the relevant data of the shop will be displayed, if you don't select the shop, the data of all shops will be displayed.




3. APP download and configuration

After clicking the icon you can scan the relevant QR code to download and configure the APP.




4. System language switch

Click on the icon to switch the system language, and click on Language Configuration to configure the translation rules for each language as required.



5. User login set up


Click on the icon to change your password and log out of your current account.



5 Shop Management

5.1 Shop List


Shop list can view all the shop information in the system, you can add new system shops and existing shops to edit, delete, and query.



5.1.1 Additional Shop


Click the Add button to add a new system shop, enter the shop number, customer shop number, shop name, and shop address, and select the organization to which it belongs (can be configured in the organizational structure) can be created successfully. Note: where with * is required.

Note: After adding a shop and registering the base station to the specified shop, the base station will be recognized online and the corresponding shop product data will be imported automatically; you can view the information of the used base station in the shop on the base station management page.




5.1.2 Edit Shop

Find the shop row that needs to be edited, and click the Edit button, you can edit the customer shop number, shop name, and shop address and change the organization it belongs to, the shop number can not be motified.




5.1.3 Search Shop

You can quickly find the shop information you are looking for by shop number, customer shop number, and shop name.



5.1.4 Delete Shop

Find the shop that needs to be deleted, and click the Delete button to delete the shop, the deletion operation requires a second confirmation from the user.




5.2 Base Station Management

After creating a shop, connect the configured base station to the network, the base station will automatically complete the registration Base station management and display the status information on the base station management page; if the base station has not completed the automatic registration for a long time, please check the network status, base station configuration, and shop configuration.


5.2.1 Query Base Station

You can quickly retrieve the base station information you need to find by shop number, base station number, and base station status.



5.2.2 Edit Base Station

Click the Edit button to change the shop to which the base station belongs and the name of the base station.




The screenshot shows the 'Base Station Management' interface. A table lists base stations with columns for Store Number, Access point, Access point name, IP, Last online time, Last offline time, Last heartbeat time, and Operate. An 'AP Management' dialog box is open, allowing users to edit the 'Store' (currently 'test(0001)') and 'Access point name' for a selected base station. The 'Operate' column contains buttons for 'Edit', 'OTA', and 'Delete'.

| Store Number | Access point | Access point name | IP | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|--------------|-------------------|--------------|-------------------|-------------------|---------------------|-----------------------|
| 0001 | 000Y | | 192.168.4.35 | 24-07-24 09:36:14 | 24-07-10 10:59:48 | 24-07-24 09:36:14 | [Edit] [OTA] [Delete] |

5.2.3 Base station OTA

If a new base station version update package has been uploaded, the selected base station can be upgraded to the current version by clicking the OTA button, and the OTA operation requires a second confirmation.




The screenshot shows the 'Base Station Management' interface with a table listing base stations. The 'Operate' column contains buttons for 'Edit', 'OTA', and 'Delete'. The 'OTA' button is highlighted, indicating the upgrade operation.

| Store Number | Access point | Access point name | IP | MAC | Status | Offline count | Firmware | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|--------------|-------------------|--------------|-------------------|--------|---------------|----------|-------------------|-------------------|---------------------|-----------------------|
| 0001 | 000Y | | 192.168.4.35 | 90-A9-F7:40:00:20 | Online | 10 | 1.0.2.23 | 24-07-24 09:36:14 | 24-07-10 10:59:48 | 24-07-24 09:36:14 | [Edit] [OTA] [Delete] |

5.2.4 Delete base station

You can delete the specified base station by clicking the Delete button, and the deletion operation requires a second confirmation.




The screenshot shows the 'Base Station Management' interface. The breadcrumb path is 'Dashboard / Store Management / Base Station Management'. There is a search bar with 'test(0001)' entered. Below the search bar is an 'Export' button. The main content is a table with the following columns: Store Number, Access point, Access point name, IP, MAC, Status, Offline count, Firmware, Last online time, Last offline time, Last heartbeat time, and Operate. The table contains one row with the following data: Store Number: 0001, Access point: 000Y, Access point name: 192.168.4.35, IP: 90-A9-F7-40:00:20, MAC: 90-A9-F7-40:00:20, Status: Online, Offline count: 10, Firmware: 1.0.7.23, Last online time: 24-07-24 09:36:14, Last offline time: 24-07-10 10:59:48, Last heartbeat time: 24-07-24 09:36:14. The 'Operate' column for this row contains three buttons: 'Edit', 'OTA', and 'Delete'. The 'Delete' button is highlighted with a red box.

| Store Number | Access point | Access point name | IP | MAC | Status | Offline count | Firmware | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|--------------|-------------------|-------------------|-------------------|--------|---------------|----------|-------------------|-------------------|---------------------|-----------------|
| 0001 | 000Y | 192.168.4.35 | 90-A9-F7-40:00:20 | 90-A9-F7-40:00:20 | Online | 10 | 1.0.7.23 | 24-07-24 09:36:14 | 24-07-10 10:59:48 | 24-07-24 09:36:14 | Edit OTA Delete |

5.2.5 Export Base Station

Click the Export button to export all the base station information under the current filter conditions.




The screenshot shows the 'Base Station Management' interface. The breadcrumb path is 'Dashboard / Store Management / Base Station Management'. There is a search bar with 'Please select a store' in the dropdown. Below the search bar is an 'Export' button, which is highlighted with a red box. The main content is a table with the following columns: Store Number, Access point, Access point name, IP, MAC, Status, Offline count, Firmware, Last online time, Last offline time, Last heartbeat time, and Operate. The table contains one row with the following data: Store Number: 0001, Access point: 000Y, Access point name: 192.168.4.35, IP: 90-A9-F7-40:00:20, MAC: 90-A9-F7-40:00:20, Status: Online, Offline count: 10, Firmware: 1.0.7.23, Last online time: 24-07-24 09:36:14, Last offline time: 24-07-10 10:59:48, Last heartbeat time: 24-07-24 09:36:14. The 'Operate' column for this row contains three buttons: 'Edit', 'OTA', and 'Delete'.

| Store Number | Access point | Access point name | IP | MAC | Status | Offline count | Firmware | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|--------------|-------------------|-------------------|-------------------|--------|---------------|----------|-------------------|-------------------|---------------------|-----------------|
| 0001 | 000Y | 192.168.4.35 | 90-A9-F7-40:00:20 | 90-A9-F7-40:00:20 | Online | 10 | 1.0.7.23 | 24-07-24 09:36:14 | 24-07-10 10:59:48 | 24-07-24 09:36:14 | Edit OTA Delete |

5.3 Electronic price tag Management


5.3.1 Add price tag

Click on the Batch Add button to select shops and then batch enter price tag IDs and add price tags to the specified shops.



The screenshot shows the 'Electronic Shelf Label Management' interface. The 'Batch Add' button is highlighted with a red box. The interface includes a sidebar with navigation options and a main table of price tags.

| Store Number | ESL ID | ESL type | UPC | Status | Signal | Temp | Communication count | Communication base station | Last Receive Time | Operate |
|--------------|--------------|-----------|--------|--------|--------|------|---------------------|----------------------------|-------------------|----------------|
| 0001 | 36000000C979 | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:07:45 | [Green] [Blue] |
| 0001 | 36000000B9F9 | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:07:00 | [Green] [Blue] |
| 0001 | 36000000B9DA | ET0213-36 | 100361 | idle | 100% | 26°C | 82 | 000Y | 24-07-23 18:06:44 | [Green] [Blue] |
| 0001 | 36000000B9A6 | ET0213-36 | 100361 | idle | 100% | 25°C | 83 | 000Y | 24-07-23 18:06:47 | [Green] [Blue] |
| 0001 | 36000000B9A8 | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:06:30 | [Green] [Blue] |
| 0001 | 36000000B9A0 | ET0213-36 | 100361 | idle | 100% | 25°C | 83 | 000Y | 24-07-23 18:06:42 | [Green] [Blue] |
| 0001 | 36000000B9F1 | ET0213-36 | 100361 | idle | 100% | 26°C | 83 | 000Y | 24-07-23 18:06:05 | [Green] [Blue] |
| 0001 | 36000000B9F8 | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:06:44 | [Green] [Blue] |
| 0001 | 36000000B9FE | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:06:47 | [Green] [Blue] |
| 0001 | 36000000B9CF | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:06:30 | [Green] [Blue] |
| 0001 | 36000000B9C0 | ET0213-36 | 100361 | idle | 100% | 26°C | 82 | 000Y | 24-07-23 18:06:42 | [Green] [Blue] |
| 0001 | 36000000B9E7 | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:06:05 | [Green] [Blue] |
| 0001 | 36000000B9E4 | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:06:44 | [Green] [Blue] |
| 0001 | 36000000C9DE | ET0213-36 | 100361 | idle | 100% | 25°C | 82 | 000Y | 24-07-23 18:06:30 | [Green] [Blue] |




The screenshot shows the 'Bulk Add' dialog box open over the price tag list. The dialog box has a title 'Bulk Add' and contains the following fields:

- * Store Number: text(0001)
- * Import Price Tags: [Empty text area]

The dialog box has 'Cancel' and 'Confirm' buttons at the bottom right.


5.3.2 Check price tag

You can quickly get the price tag you need to search according to the shop number, price tag ID, bound product UPC, price tag type, bound status, and price tag status.




5.3.3 Refresh price tag

Tick the price tags that need to be refreshed at the bottom of the list of electronic price tags and click the Refresh button to refresh the price tags in batch, and the latest status information of the price tags will be displayed after refreshing.




5.3.4 Delete price tag


Tick the price tags that need to be deleted below the list of electronic price tags and click the Delete button to delete the price tags in batches.



5.3.5 price tag flash



After ticking the price tags that need to flash under the list of electronic price tags and clicking the flash button, you can set the color and duration of the flashing light of the price tags in batch, which is convenient for users to locate the price tags quickly.






5.3.6 Price tag import and export

Click the Import button to select the specified shop and upload the price tag Excel file to import the price tag and the binding relationship between the price tag and the product, tick to override the existing binding relationship will be based on the latest price tag binding relationship in the file.





Click the Export button to export all price tag and price tag binding relationship data.




5.3.7 Product Binding and Unbinding

Click on the corresponding price tag line of the binding button, and enter the product UPC can be bound to the product (you need to add product information in the system product management module), if the price tag is bound to a multi-product template, you need to enter more than one product UPC binding.





Tick the labels that need to be unbound in the list of electronic price tags and click the Unbind button to batch unbind the products.



5.3.8 Combine Template Binding

When the price tag needs to be bound to more than one product, you need to use the combination binding and click the combination binding button to select the multiple product templates that the price tag needs to be bound to.




5.4 Digital Signage Management

After creating the shop, connect the configured digital signage to the network, and the digital signage will automatically access the system and display the status information in the list; if the digital signage has not been online for a long time, please check the network status as well as the equipment situation.

5.4.1 Check price tag

You can quickly find the price tag you need to search by shop number, price tag ID, bound product code, template name, price tag status, region, and screen status.




The screenshot shows the 'Digital Signage Management' interface. A search bar at the top contains fields for 'Tag ID', 'Goods Code', 'Template name', 'Status', 'Select area', and 'LCD Status', with a 'Search' button. Below the search bar is a table with the following columns: Tag ID, Store Number, Area Belong, Goods ID, Show template, Status, LCD Status, Last heartbeat time, Last download time, Time consuming, Firmware version, and Operate. Two rows of data are visible in the table.

| Tag ID | Store Number | Area Belong | Goods ID | Show template | Status | LCD Status | Last heartbeat time | Last download time | Time consuming | Firmware version | Operate |
|--------------|--------------|-------------|----------------------|---------------|--------|------------|---------------------|--------------------|----------------|------------------|--|
| 00080014862E | 0001 | 生鲜区 | 100543 | 视频+商品x1 | Online | Screen On | 24-07-23 18:06:35 | 24-07-23 18:06:26 | 45s | 92 | + - + |
| 00080016177B | 0001 | 生鲜区 | 102906 102344 100233 | 10.3个商品 | Online | Screen On | 24-07-23 10:57:20 | 24-07-23 10:57:03 | 1min25s | 92 | + - + |


5.4.2 Import and export price tag

Click the Import button to import the MAC address of the price tag as an Excel file to get the device information.




The screenshot shows the same 'Digital Signage Management' interface as above, but with the 'Import' button in the top toolbar highlighted with a red box. The table below it contains the same two rows of data as in the previous screenshot.

| Tag ID | Store Number | Area Belong | Goods ID | Show template | Status | LCD Status | Last heartbeat time | Last download time | Time consuming | Firmware version | Operate |
|--------------|--------------|-------------|----------------------|---------------|--------|------------|---------------------|--------------------|----------------|------------------|--|
| 00080014862E | 0001 | 生鲜区 | 100543 | 视频+商品x1 | Online | Screen On | 24-07-23 18:06:35 | 24-07-23 18:06:26 | 45s | 92 | + - + |
| 00080016177B | 0001 | 生鲜区 | 102906 102344 100233 | 10.3个商品 | Online | Screen On | 24-07-23 10:57:20 | 24-07-23 10:57:03 | 1min25s | 92 | + - + |




Click the initial button to export all the digital signage lists under the current filter.




SMART TAG LEADER


5.4.3 Product Bind and Unbind

You can set the region to which the price tag belongs and select the product ID you want to bind by clicking the Bind button corresponding to the price tag.






Tick the digital signage in the list and click the Unbind button to batch unbind the signage and merchandise.



5.4.4 Screen on and screen off

Tick the price tag at the bottom of the list to bulk control the device's Screen on and screen off.



5.4.5 Synchronize device status

Click the Sync Status button to manually synchronize all device statuses.

The screenshot shows the 'Digital Signage Management' dashboard. The left sidebar contains a menu with 'Digital Signage Management' highlighted in red. The main content area displays a table of devices with columns for Tag ID, Store Number, Area Belong, Goods ID, Show template, Status, LCD Status, Last heartbeat time, Last download time, Time consuming, Firmware version, and Operate. A 'Sync Status' button is highlighted in a red box above the table.

| Tag ID | Store Number | Area Belong | Goods ID | Show template | Status | LCD Status | Last heartbeat time | Last download time | Time consuming | Firmware version | Operate |
|-------------|--------------|-------------|----------------------|---------------|--------|------------|---------------------|--------------------|----------------|------------------|---|
| 00000148B2E | 0001_2 | 生鲜区 | 100543 | 视频-商品X1 | Online | Screen On | 24-07-23 18:06:35 | 24-07-23 18:06:26 | 45s | 92 | + - ⌵ ⌶ |
| 0000016177B | 0001_2 | 生鲜区 | 102906 102344 100233 | 10.13个商品 | Online | Screen On | 24-07-23 10:57:20 | 24-07-23 10:57:03 | 1min25s | 92 | + - ⌵ ⌶ |

5.4.6 Refresh price tag



Tick the price tag at the bottom of the list and click the Refresh button to batch-refresh the price tag information.

The screenshot shows the 'Digital Signage Management' dashboard. The left sidebar contains a menu with 'Digital Signage Management' highlighted in red. The main content area displays a table of devices. The 'Refresh' button is highlighted in a red box above the table.

| Tag ID | Store Number | Area Belong | Goods ID | Show template | Status | LCD Status | Last heartbeat time | Last download time | Time consuming | Firmware version | Operate |
|-------------|--------------|-------------|----------------------|---------------|--------|------------|---------------------|--------------------|----------------|------------------|---|
| 00000148B2E | 0001_2 | 生鲜区 | 100543 | 视频-商品X1 | Online | Screen On | 24-07-23 18:06:35 | 24-07-23 18:06:26 | 45s | 92 | + - ⌵ ⌶ |
| 0000016177B | 0001_2 | 生鲜区 | 102906 102344 100233 | 10.13个商品 | Online | Screen On | 24-07-23 10:57:20 | 24-07-23 10:57:03 | 1min25s | 92 | + - ⌵ ⌶ |


5.4.7 Delete price tag


You can choose to delete the device in the system or restore the factory settings by clicking the Delete button of the corresponding price tag.



5.4.8 Preview price tag

Click on the preview button corresponding to the price tag to preview the content displayed for that device.









5.5 Area Management

5.5.1 Adding Area and Sub-Area

Click on the Add button to create a new area for the specified shop. The area can be used to manage the partition to which the price tag belongs.




Child areas can be added under the parent area by clicking the Add button corresponding to that area.




5.5.2 Edit area

You can edit the shop to which the area belongs and the name of the area by clicking the Edit button corresponding to the area.




5.5.3 Delete area

Click the Delete button to delete the specified area




5.5.4 Bound area material


1. Click the Binding button of the corresponding area to enter the material binding page.




2. Select a category on the left or enter a clip name or select a clip type above to find the desired clip.




3. Select the material you want to bind click the Add button to bind the material, and turn on the Default switch to set the material as the default material.



4. You can click the button as shown in the picture to set the bound clip as the default clip.




5. Click the Delete button to delete the clip.



5.6 Advertisement screen management

5.6.1 Enquiry Device

You can quickly retrieve the equipment you want to query based on the shop it belongs to, region, equipment size, equipment model, equipment name, and equipment status.




The screenshot shows the 'Advertising Screen Management' interface. At the top, there is a search bar with filters for 'Please select a store', 'Select area', 'Device Size', 'Device model', 'Device name', and 'Device status', along with a 'Search' button. Below the search bar, there are buttons for 'Delete', 'Refresh', and 'Unbind'. The main area contains a table with the following columns: Store Number, Device ID, Device name, Device model, IP, Size, Monitor Count, Template name, Device status, Firmware version, Last online time, Last offline time, Last heartbeat time, and Operate. The table lists several devices, including those with 'Online' and 'Offline' statuses.


| Store Number | Device ID | Device name | Device model | IP | Size | Monitor Count | Template name | Device status | Firmware version | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|------------------|-------------|--------------------------|--------------|-------------|---------------|------------------|---------------|------------------|------------------|-------------------|---------------------|---|
| 0001 | 0a714dc4b9788225 | -- | WYST-1972-WYS T-1972 | 192.168.4.20 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | 208aa6521de93358 | -- | WYST-1972-WYS T-1972 | 192.168.4.32 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | 4be23f1f649cbf7 | -- | WYST-1972-WYS T-1972 | 192.168.4.8 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.51 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | 66ee19283b85d2f9 | -- | WYST-1972-WYS T-1972 | 192.168.4.7 | 2880 * 158 | 1 | U | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | 691913ad9c5b8909 | -- | WYST-1972-WYS T-1972 | 192.168.4.21 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | 74f8d4fec514164 | -- | WYST-1972-WYS T-1972 | 192.168.4.27 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | 752856b1aaeebc | -- | Droidlogic-8T29 D3CU-HKC | 192.168.4.4 | 1920 * 540 | 1 | 1920x540商品1 | Offline | 3.1.52 | 07-24 10:10 | 07-24 10:10 | 07-24 10:08 | + - ↺ ↻ |
| 0001 | 7836f72d9d74574d | -- | WYST-1972-WYS T-1972 | 192.168.4.6 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | d5b1260f42b5a7ee | 广告屏测试 | Actions-5700 | 192.168.4.33 | 1080 * 1920 | 2 | Side ACU Side B: | Online | 3.1.52 | 07-23 18:37 | 07-23 13:28 | 07-24 10:26 | + - ↺ ↻ |
| 0001 | dc43b0d1619b923 | -- | WYST-1972-WYS T-1972 | 192.168.4.28 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | + - ↺ ↻ |

5.6.2 Product Bind and Unbind


You can set the binding area of the device and the product ID you want to bind by clicking the corresponding device's binding button, and the product ID supports binding multiple products. After binding, the system will automatically match the template according to the size of the device and the number of bound products.




The screenshot shows the same 'Advertising Screen Management' interface as above. A red box highlights the 'Operate' column for the first device (Device ID: 0a714dc4b9788225), specifically the binding button (represented by a red square with a white plus sign).



You can unbind the product binding information of a device by clicking the unbind button corresponding to the device.



You can also tick the devices you want to unbind and click the Unbind button to batch unbind the product binding relationship.



5.6.3 Advertising Screen Editor

You can edit the device name by clicking the Edit button corresponding to the device.

| Store Number | Device ID | Device name | Device model | IP | Size | Monitor Count | Template name | Device status | Firmware version | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|------------------|-------------|-------------------------|--------------|-------------|---------------|---------------------|---------------|------------------|------------------|-------------------|---------------------|---------|
| 0001 | 0a714dc489788225 | -- | WYST-T972-WYST-T972 | 192.168.4.20 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Edit] |
| 0001 | 208aa6521de93358 | -- | WYST-T972-WYST-T972 | 192.168.4.32 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Edit] |
| 0001 | 4be23f1f649cbf7 | -- | WYST-T972-WYST-T972 | 192.168.4.3 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.51 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Edit] |
| 0001 | 66ee19283b85d2f9 | -- | WYST-T972-WYST-T972 | 192.168.4.7 | 2880 * 158 | 1 | U | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Edit] |
| 0001 | 691913ad9c5b8909 | -- | WYST-T972-WYST-T972 | 192.168.4.21 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Edit] |
| 0001 | 74f8d4fec514164 | -- | WYST-T972-WYST-T972 | 192.168.4.27 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Edit] |
| 0001 | 752856b1aaeebc | -- | Droidlogic-8T29D3CN-HKC | 192.168.4.4 | 1920 * 540 | 1 | 1920x540设备1 | Offline | 3.1.52 | 07-24 10:10 | 07-24 10:10 | 07-24 10:08 | [Edit] |
| 0001 | 7836f72d9d74574d | -- | WYST-T972-WYST-T972 | 192.168.4.6 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Edit] |
| 0001 | d5b1260f42b5a7ee | 广告屏测试 | Actions-S700 | 192.168.4.33 | 1080 * 1920 | 2 | Side A:U Side B: | Online | 3.1.52 | 07-23 18:37 | 07-23 13:28 | 07-24 10:26 | [Edit] |
| 0001 | dc43b0d16198a923 | -- | WYST-T972-WYST-T972 | 192.168.4.28 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Edit] |

Advertisement screen modification

Device ID: 4be23f1f649cbf7

* Device name:

Device model: WYST-T972-WYST-T972

5.6.4 Advertising Screen Preview

Click the preview button corresponding to the device you want to preview to view the effect of the device content display.

Dashboard / Store Management / Advertising Screen Management

Please select a store | Select area | Device Size | Device model | Device name | Device status | Search

Delete Refresh Unbind

| Store Number | Device ID | Device name | Device model | IP | Size | Monitor Count | Template name | Device status | Firmware version | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|------------------|-------------|-------------------------|--------------|-------------|---------------|-----------------|---------------|------------------|------------------|-------------------|---------------------|-----------|
| 0001 | 0a714dc489788225 | -- | WYST-T972-WYS T-7972 | 192.168.4.20 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | 208aa6521de93358 | -- | WYST-T972-WYS T-7972 | 192.168.4.32 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |
| 0001 | 4be23f1f649cbf7 | -- | WYST-T972-WYS T-7972 | 192.168.4.8 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.51 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | 66ee19283b85d2f9 | -- | WYST-T972-WYS T-7972 | 192.168.4.7 | 2880 * 158 | 1 | U | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | 691913ad9c5b8909 | -- | WYST-T972-WYS T-7972 | 192.168.4.21 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |
| 0001 | 74f8d4fec514164 | -- | WYST-T972-WYS T-7972 | 192.168.4.27 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |
| 0001 | 752856b1aaeebccc | -- | Droologic-8729 D3CN-HKC | 192.168.4.4 | 1920 * 540 | 1 | 1920x540(商品) | Offline | 3.1.52 | 07-24 10:10 | 07-24 10:10 | 07-24 10:08 | [Preview] |
| 0001 | 7836f72d9d74574d | -- | WYST-T972-WYS T-7972 | 192.168.4.6 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | d5b1260f42b5a7ee | 广告屏测试 | Actions-S700 | 192.168.4.33 | 1080 * 1920 | 2 | Side A/U Side B | Online | 3.1.52 | 07-23 18:37 | 07-23 13:28 | 07-24 10:26 | [Preview] |
| 0001 | d643b0d1619b8923 | -- | WYST-T972-WYS T-7972 | 192.168.4.28 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |

Dashboard / Store Management / Advertising Screen Management

Please select a store | Select area | Device Size | Device model | Device name | Device status | Search



Device Content Preview

Side A

| Store Number | Device ID | Device name | Device model | IP | Size | Monitor Count | Template name | Device status | Firmware version | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|------------------|-------------|-------------------------|--------------|-------------|---------------|-----------------|---------------|------------------|------------------|-------------------|---------------------|-----------|
| 0001 | 0a714dc489788225 | -- | WYST-T972-WYS T-7972 | 192.168.4.20 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | 208aa6521de93358 | -- | WYST-T972-WYS T-7972 | 192.168.4.32 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |
| 0001 | 4be23f1f649cbf7 | -- | WYST-T972-WYS T-7972 | 192.168.4.8 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.51 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | 66ee19283b85d2f9 | -- | WYST-T972-WYS T-7972 | 192.168.4.7 | 2880 * 158 | 1 | U | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | 691913ad9c5b8909 | -- | WYST-T972-WYS T-7972 | 192.168.4.21 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |
| 0001 | 74f8d4fec514164 | -- | WYST-T972-WYS T-7972 | 192.168.4.27 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |
| 0001 | 752856b1aaeebccc | -- | Droologic-8729 D3CN-HKC | 192.168.4.4 | 1920 * 540 | 1 | 1920x540(商品) | Offline | 3.1.52 | 07-24 10:10 | 07-24 10:10 | 07-24 10:08 | [Preview] |
| 0001 | 7836f72d9d74574d | -- | WYST-T972-WYS T-7972 | 192.168.4.6 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | [Preview] |
| 0001 | d5b1260f42b5a7ee | 广告屏测试 | Actions-S700 | 192.168.4.33 | 1080 * 1920 | 2 | Side A/U Side B | Online | 3.1.52 | 07-23 18:37 | 07-23 13:28 | 07-24 10:26 | [Preview] |
| 0001 | d643b0d1619b8923 | -- | WYST-T972-WYS T-7972 | 192.168.4.28 | 2880 * 158 | 1 | 2880 * 158 | Online | 3.1.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | [Preview] |

5.6.5 Remote control

Remote control commands can be output for scheduling devices by clicking the remote control button corresponding to the device.



5.6.6 Delete Device

Tick the devices you want to delete and click the Delete button to delete the device information in bulk.

Dashboard / Store Management / Advertising Screen Management

Please select a store

Please select a store | SELECT Area | Device Size | Device model | Device name | Device status | Search

Delete Refresh Unbind

| Store Number | Device ID | Device name | Device model | IP | Size | Monitor Count | Template name | Device status | Firmware version | Last online time | Last offline time | Last heartbeat time | Operate |
|--------------|------------------|-------------|--------------------------|--------------|---------------|---------------|---------------------|---------------|------------------|------------------|-------------------|---------------------|---------|
| 0001 | 0a714dc4597b8225 | -- | WYS1-T972-WYS1-T972 | 192.168.4.20 | 2880*158 | 1 | 2880*158 | Online | 3.3.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | Operate |
| 0001 | 208aa6521d493358 | -- | WYS1-T972-WYS1-T972 | 192.168.4.32 | 2880*158 | 1 | 2880*158 | Online | 3.3.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | Operate |
| 0001 | 4be23f17649c077 | -- | WYS1-T972-WYS1-T972 | 192.168.4.18 | 2880*158 | 1 | 2880*158 | Online | 3.3.51 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | Operate |
| 0001 | 66ee192830585d99 | -- | WYS1-T972-WYS1-T972 | 192.168.4.7 | 2880*158 | 1 | U | Online | 3.3.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | Operate |
| 0001 | 691913ad9c5b8909 | -- | WYS1-T972-WYS1-T972 | 192.168.4.21 | 2880*158 | 1 | 2880*158 | Online | 3.3.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | Operate |
| 0001 | 74fb84dfec514164 | -- | WYS1-T972-WYS1-T972 | 192.168.4.27 | 2880*158 | 1 | 2880*158 | Online | 3.3.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | Operate |
| 0001 | 752856b1aaeebc | -- | Orindlogic-BT29-03CN-HKC | 192.168.4.4 | 1920*540(商品1) | 1 | 1920*540(商品1) | Offline | 3.3.52 | 07-24 10:10 | 07-24 10:10 | 07-24 10:08 | Operate |
| 0001 | 7836f72d9d74574d | -- | WYS1-T972-WYS1-T972 | 192.168.4.16 | 2880*158 | 1 | 2880*158 | Online | 3.3.52 | 07-23 18:37 | 07-23 09:44 | 07-24 10:26 | Operate |
| 0001 | d5b1260f42b5a7ee | 广告屏测试 | Actions-S700 | 192.168.4.33 | 1080*1920 | 2 | Side A:U Side B: | Online | 3.3.52 | 07-23 18:37 | 07-23 13:28 | 07-24 10:26 | Operate |
| 0001 | dc43b0d16198a923 | -- | WYS1-T972-WYS1-T972 | 192.168.4.28 | 2880*158 | 1 | 2880*158 | Online | 3.3.52 | 07-23 18:37 | 07-23 09:42 | 07-24 10:26 | Operate |

5.7 Video Service Management

5.7.1 Enquiry Service

You can filter by shop to see all video services under that shop.

Dashboard / Store Management / Video Service Management

Please select a store

Please select a store | Search

| Store Number | Video service IP | Service type | Temperature (°C) | Version | Last heartbeat time | Status | Online times | Creation Time | Operate |
|--------------|-------------------|-----------------|------------------|----------|----------------------|--------|--------------|-------------------|---------|
| All stores | 192.168.4.23:3001 | TFT API service | | 3.3.21.0 | 07-24 07-24 10:47:07 | Online | 5 | 24-07-11 16:15:15 | Operate |
| All stores | 192.168.4.23:3002 | Video service | Unknown | 3.3.19.0 | 07-24 07-24 10:46:17 | Online | 4 | 24-07-11 16:15:26 | Operate |

5.7.2 Delete Service

Click the Delete button for the service you want to delete.

The screenshot shows the 'Video Service Management' page. The left sidebar has 'Video Service Management' highlighted. The main area contains a table with the following data:

| Store Number | Video service IP | Service type | Temperature (°C) | Version | Last heartbeat time | Status | Online times | Creation Time | Operate |
|--------------|-------------------|-----------------|------------------|----------|---------------------|--------|--------------|-------------------|----------|
| All stores | 192.168.4.23:3001 | TFT API service | | 3.1.21.0 | 24-07-24 10:47:07 | Online | 5 | 24-07-11 16:15:15 | [Delete] |
| All stores | 192.168.4.23:3002 | Video service | Unknown | 3.1.19.0 | 24-07-24 10:46:17 | Online | 4 | 24-07-11 16:15:26 | [Delete] |

6 Data management

6.1 Product Management

6.1.1 Custom List

Click the List Settings button to freely set the product fields that the list wants to display.


The screenshot shows the 'Product Management' page. The left sidebar has 'Product Management' highlighted. The main area contains a table with the following data:

| Store | Goods Name | Goods Code | Template | UPC | | | | | |
|-------|------------|------------|----------|----------------------|--|--|-------------------|--|--|
| 0001 | 大平担刺猪11 | 100010 | REG | 100010,4589484761233 | | | | | |
| 0001 | 118g开心果 | 100005 | REG | 100005,6930044166209 | | | | | |
| 0001 | 爱德熊指吾乳饮品 | 10 | REG | 10,40338576 | | | 24-07-23 18:05:39 | | |
| 0001 | 四季宝颗粒花生香 | 100 | REG | 100,2100010000002 | | | 24-07-23 18:05:39 | | |
| 0001 | 黄冰糖 | 100361 | REG | 100361,6934848931117 | | | 24-07-23 18:05:39 | | |
| 0001 | 劲霸味冰爽味 | 100543 | REG | 100543,490288343254 | | | 24-07-23 18:05:39 | | |
| 0001 | 888 | 10101010 | REG | 10101010,2020020 | | | 24-07-22 13:43:32 | | |
| 0001 | AAA | 87564331 | REG | 87564331,3346578 | | | 24-07-22 10:30:29 | | |
| 0001 | 68g烤鱼片 | 100001 | REG | 100001,6930044167336 | | | 24-07-18 23:10:47 | | |
| 0001 | 蒙恬薯饼干 | 100391 | REG | 100391,6934848961664 | | | 24-07-17 13:20:59 | | |
| 0001 | 核桃夹心多员糖 | 102406 | REG | 102406,4589892550849 | | | 24-07-17 13:20:53 | | |
| 0001 | 阿诺哥小米奇饼干 | 1356 | REG | 1356,8412674104038 | | | 24-07-16 15:52:38 | | |
| 0001 | 生菓300g | 102048 | REG | 102048,2110204800004 | | | 24-07-16 15:47:34 | | |
| 0001 | 维他奶舒片(塔塔) | 10201 | REG | 10201,8997788990659 | | | 24-07-16 14:57:03 | | |
| 0001 | 蜜悦原浆 | 102010 | REG | 102010,2383184700011 | | | 24-07-16 14:57:03 | | |

A red box highlights the 'List Settings' button in the top right corner of the table area.


6.1.2 Enquiry Product


You can quickly retrieve the product information you want to search by shop, product code, product name, product UPC, and template type.



6.1.3 Add Product



Click the Add button and enter the product information to add products to the specified shop (product fields need to be configured in the initialization of the system), where the template type and shop name must be selected.





6.1.4 Edit Product

Product information can be modified by clicking the Edit button corresponding to the product, shop information cannot be modified.

























Dashboard / Data Management / Product Management

Please select a store

test(0001) Goods Code Goods Name UPC Template Type Search

+ Add Import Export Bind Export Resource Binding Import Resource Binding

| Store | Goods Name | Goods Code | Template | UPC | Last Update Time | Operate |
|-------|------------|------------|----------|----------------------|-------------------|---|
| 0001 | 大平招财猫33 | 100010 | REG | 100010,4589484761233 | 24-07-24 12:00:00 |   |
| 0001 | 118g开心果 | 100005 | REG | 100005,6930044166209 | 24-07-23 18:05:39 |   |
| 0001 | 卓德脱脂含乳饮品 | 10 | REG | 10,40338576 | 24-07-23 18:05:39 |   |
| 0001 | 四季宝颗粒花生酱 | 100 | REG | 100,2100010000002 | 24-07-23 18:05:39 |   |
| 0001 | 黄冰糖 | 100361 | REG | 100361,6934848931117 | 24-07-23 18:05:39 |   |
| 0001 | 奶酷棒冰淇淋 | 100543 | REG | 100543,4902888343254 | 24-07-23 18:05:39 |   |
| 0001 | BBB | 10101010 | REG | 10101010,2020020 | 24-07-22 13:43:32 |   |
| 0001 | AAA | 87564331 | REG | 87564331,13346578 | 24-07-22 10:38:29 |   |
| 0001 | 68g烤鱼片 | 100001 | REG | 100001,6930044167336 | 24-07-18 23:10:47 |   |
| 0001 | 豪雄葡萄干 | 100391 | REG | 100391,6934848961664 | 24-07-17 13:38:59 |   |
| 0001 | 桔梗花4.0多用碗 | 102406 | REG | 102406,4589892550849 | 24-07-17 13:28:53 |   |

6.1.5 Delete Product































Click the Delete button to delete the specified product.

Dashboard / Data Management / Product Management

Please select a store



Please select a store Goods Code Goods Name UPC Template Type Search

+ Add Import Export Bind Export Resource Binding Import Resource Binding


| Store | Goods Name | Goods Code | Template | UPC | Last Update Time | Operate |
|-------|------------|------------|----------|----------------------|-------------------|---|
| 0001 | 大平招财猫11 | 100010 | REG | 100010,4589484761233 | 24-07-24 00:00:00 |   |
| 0001 | 118g开心果 | 100005 | REG | 100005,6930044166209 | 24-07-23 18:05:39 |   |
| 0001 | 卓德脱脂含乳饮品 | 10 | REG | 10,40338576 | 24-07-23 18:05:39 |   |
| 0001 | 四季宝颗粒花生酱 | 100 | REG | 100,2100010000002 | 24-07-23 18:05:39 |   |
| 0001 | 黄冰糖 | 100361 | REG | 100361,6934848931117 | 24-07-23 18:05:39 |   |
| 0001 | 奶酷棒冰淇淋 | 100543 | REG | 100543,4902888343254 | 24-07-23 18:05:39 |   |
| 0001 | BBB | 10101010 | REG | 10101010,2020020 | 24-07-22 13:43:32 |   |
| 0001 | AAA | 87564331 | REG | 87564331,13346578 | 24-07-22 10:38:29 |   |
| 0001 | 68g烤鱼片 | 100001 | REG | 100001,6930044167336 | 24-07-18 23:10:47 |   |
| 0001 | 豪雄葡萄干 | 100391 | REG | 100391,6934848961664 | 24-07-17 13:38:59 |   |
| 0001 | 桔梗花4.0多用碗 | 102406 | REG | 102406,4589892550849 | 24-07-17 13:28:53 |   |
| 0001 | 阿波那小米香饼干 | 1366 | REG | 1366,8412674104036 | 24-07-16 15:52:36 |   |
| 0001 | 生菜300g | 102048 | REG | 102048,2110204800004 | 24-07-16 15:47:34 |   |
| 0001 | 御海源虾片(海苔) | 10201 | REG | 10201,899788990659 | 24-07-16 14:57:03 |   |
| 0001 | 餐饮原料 | 102010 | REG | 102010,2303164700011 | 24-07-16 14:57:03 |   |

6.1.6 Product Import and Export

Click the Import button to select a shop and upload the product information file to import the products into the designated shop.




Select the shop data you want to export and click the Export button to export all the product information under that shop.




6.1.7 Product Material Bind


1. Click the Binding button of the product you want to bind to open the binding page.




2. Search for the product material you want to bind according to the categories on the left and the search criteria on the top.



3. Select the material you want to bind and click the Add button to bind it successfully.




4. After successful binding, you can choose to set the clip as the default clip or delete the clip.




6.1.8 Quick Bind


1. Click the Bind button to open the Quick Bind page.



2. Find the product you want to bind according to the query conditions, click the product, and then select the material you want to bind on the right side and click the bind button to bind successfully.




3. Click the Unbind button to quickly unbind a product.





6.1.9 Import and export clip bind

Select the shop you want to export and click the Export Material Bindings button to export the material and product bindings for that shop.





Click the Import Material Binding button, you can select the bind relationship between the shop's imported products and materials.



6.2 Plan Task



6.2.1 Add Task

Click the Add button to add a scheduled task for merchandise information change to the specified shop. The task will change the merchandise information at the specified time and restore the merchandise information at the specified time.




6.2.2 Modify Task

You can modify the task execution time and recovery time by clicking the Edit button for tasks that have not been started.



6.2.3 Delete Task


A task not started can be deleted directly by clicking the Delete button.



6.3 Material Management



6.3.1 Enquiry Material

You can quickly retrieve the material you need to query by resource classification, material classification, review status, material name, material keywords.





6.3.2 Upload material

Click the Upload Material button to select the material file to upload, when the shop is selected and ticked to cover the current label record will automatically update the material bound to the product.




6.3.3 Material Classification Management

You can add, edit, and delete clip categories by clicking the clip category management button.




6.3.4 Edit material

Click on the edit button of the clip to modify the clip label, feature code, and search keywords.




6.3.5 Review Material

Users with auditing privileges can click on the Audit button of the material for auditing, and only the audited material can be officially used.




Click the Select All button on this page to batch-select the clips that need to be reviewed, and click the One Click Review button to review them successfully.




6.3.6 Delete material

You can delete a clip by clicking the clip's Delete button.




You can delete the clips you want to delete with one click by clicking Select All on this page.




6.3.7 Online material

Click the download button to download the material you want, or you can tick the material you want to download in bulk.




Click on the download list to see the progress of the download.





6.4 Display Management

6.4.1 Check price tag

You can query the display information of the product according to the shop, shelf number, product ID, product name, and price tag ID.





Click on a shelf's View button to see the display information for that shelf.




6.4.2 Import display information

Click the Import button to import the price tag display information of the selected shop.



6.4.3 Delete shelf

Click the Delete button to delete the shelf information and the corresponding display data.



7 Data query

7.1 Electronic price tag communication records

7.1.1 Enquiry Record

You can quickly retrieve the required communication records based on shop, price tag ID, product ID, price tag type, communication type, communication status, and last send time.

The screenshot shows the 'Electronic Shelf Label Communication Log' interface. At the top, there is a search bar with fields for 'Please select a store', 'ESL ID', 'Goods ID', 'ESL type', 'Communication', 'Communication', 'Start Time', and 'End Time', along with a 'Search' button. Below the search bar is a table with the following columns: Store Number, ESL ID, ESL type, ESL Template, UPC, Communication Type, Communication Status, a signal strength indicator, a temperature indicator, Creation Time, Last sent time, Time consuming, Communication base station, and Operate. The table contains 18 rows of data, each representing a communication record.

| Store Number | ESL ID | ESL type | ESL Template | UPC | Communication Type | Communication Status | Signal | Temp | Creation Time | Last sent time | Time consuming | Communication base station | Operate |
|--------------|--------------|-----------|--------------|--------|--------------------|----------------------|--------|------|-------------------|-------------------|----------------|----------------------------|---------|
| 0001 | 4000000E4A0 | ET0420-40 | Q05 | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 24 | 000Y(1) | Operate |
| 0001 | 4000000E4A23 | ET0420-40 | Q05 | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 50 | 000Y(1) | Operate |
| 0001 | 820000219E03 | ET0266-82 | REG | 100543 | Data | Success | 100% | 24°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 67 | 000Y(1) | Operate |
| 0001 | 3600000B8A9A | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 50 | 000Y(1) | Operate |
| 0001 | 810000270E00 | ET0213-81 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 36000001498A | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | Operate |
| 0001 | 360000015EA3 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 36000000C6B0 | ET0213-36 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 62 | 000Y(1) | Operate |
| 0001 | 36000000B8F8 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 36000000B8F1 | ET0213-36 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | Operate |
| 0001 | 4000000E4A2 | ET0420-40 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 360000015EB4 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 36000000CA33 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 50 | 000Y(1) | Operate |

7.1.2 Preview Price Tag

Click on the Preview button to preview the contents of the price tag display at the time of this communication.

The screenshot shows the same 'Electronic Shelf Label Communication Log' interface as above. In this view, the 'Operate' column for the first row (Store Number 0001, ESL ID 4000000E4A0) has a red box highlighting the 'Preview' button.

| Store Number | ESL ID | ESL type | ESL Template | UPC | Communication Type | Communication Status | Signal | Temp | Creation Time | Last sent time | Time consuming | Communication base station | Operate |
|--------------|--------------|-----------|--------------|--------|--------------------|----------------------|--------|------|-------------------|-------------------|----------------|----------------------------|---------|
| 0001 | 4000000E4A0 | ET0420-40 | Q05 | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 24 | 000Y(1) | Preview |
| 0001 | 4000000E4A23 | ET0420-40 | Q05 | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 50 | 000Y(1) | Operate |
| 0001 | 820000219E03 | ET0266-82 | REG | 100543 | Data | Success | 100% | 24°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 67 | 000Y(1) | Operate |
| 0001 | 3600000B8A9A | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 50 | 000Y(1) | Operate |
| 0001 | 810000270E00 | ET0213-81 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 36000001498A | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | Operate |
| 0001 | 360000015EA3 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 36000000C6B0 | ET0213-36 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 62 | 000Y(1) | Operate |
| 0001 | 36000000B8F8 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 36000000B8F1 | ET0213-36 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | Operate |
| 0001 | 4000000E4A2 | ET0420-40 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |
| 0001 | 360000015EB4 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | Operate |

| Store Number | ESI ID | ESI type | ESI Template | UPC | Communication type | Communication Status | Signal strength | Temperature | Creation Time | Last sent time | Time consuming | Communication base station | Operate |
|--------------|--------------|-----------|--------------|--------|--------------------|----------------------|-----------------|-------------|-------------------|-------------------|----------------|----------------------------|---------|
| 0001 | 40000008440 | ET0420-40 | Q05 | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 24 | 000Y(1) | |
| 0001 | 40000008A23 | ET0420-40 | Q05 | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 50 | 000Y(1) | |
| 0001 | 82000219E03 | ET0266-82 | REG | 100543 | Data | Success | 100% | 24°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 67 | 000Y(1) | |
| 0001 | 36000008A8A | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:41 | 24-07-23 18:05:41 | 50 | 000Y(1) | |
| 0001 | 81000270E00 | ET0213-81 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | |
| 0001 | 3600001498A | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | |
| 0001 | 36000015EA3 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | |
| 0001 | 3600000C868 | ET0213-36 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 52 | 000Y(1) | |
| 0001 | 360000008B8 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | |
| 0001 | 360000008F1 | ET0213-36 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | |
| 0001 | 400000084A2 | ET0420-40 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | |
| 0001 | 360000015E8A | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 64 | 000Y(1) | |
| 0001 | 36000000CA33 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 50 | 000Y(1) | |
| 0001 | 80000270F54 | ET0154-80 | REG | 100361 | Data | Success | 100% | 26°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | |
| 0001 | 360000015BA0 | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 67 | 000Y(1) | |
| 0001 | 36000000C84D | ET0213-36 | REG | 100361 | Data | Success | 100% | 25°C | 24-07-23 18:05:40 | 24-07-23 18:05:41 | 24 | 000Y(1) | |

7.2 Digital Signage Communication Records

7.2.1 Enquiry record

You can quickly retrieve the communication records you need based on shop, area name, device ID, task type, and video drop status.

| Store Number | Area Belong | Device ID | Bound Goods | Video Send Status | Task Type | Creation Time | Download Time | Verify Time | Confirm Time (seconds) | Operate |
|--------------|-------------|--------------|---------------------|-------------------|----------------|-------------------|-------------------|-------------------|------------------------|---------|
| 0001 | 生鲜区 | 000B0014882E | 100543, 100, 100002 | Build Success | Update Display | 24-07-24 10:03:55 | 24-07-24 10:05:04 | 24-07-24 10:05:04 | 1min9s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 18:05:41 | 24-07-23 18:06:26 | 24-07-23 18:06:27 | 45s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 18:05:41 | 24-07-23 18:06:26 | 24-07-23 18:06:27 | 45s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 17:57:38 | 24-07-23 17:58:36 | 24-07-23 17:58:37 | 58s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 17:57:38 | 24-07-23 17:58:36 | 24-07-23 17:58:36 | 58s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 17:49:21 | 24-07-23 17:50:48 | 24-07-23 17:50:48 | 1min27s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 17:24:25 | 24-07-23 17:25:31 | 24-07-23 17:25:33 | 1min7s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 17:24:25 | 24-07-23 17:25:31 | 24-07-23 17:25:34 | 1min8s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 17:12:55 | 24-07-23 17:12:55 | 24-07-23 17:12:55 | 1s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 16:27:46 | 24-07-23 16:28:48 | 24-07-23 16:28:48 | 1min2s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 16:27:46 | 24-07-23 16:28:48 | 24-07-23 16:28:48 | 1min2s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 16:25:41 | 24-07-23 16:27:13 | 24-07-23 16:27:14 | 1min32s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 16:25:41 | 24-07-23 16:27:13 | 24-07-23 16:27:14 | 1min32s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 16:17:20 | 24-07-23 16:19:24 | 24-07-23 16:19:25 | 2min4s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Build Success | Update Display | 24-07-23 16:17:20 | 24-07-23 16:19:24 | 24-07-23 16:19:25 | 2min4s | |
| 0001 | 生鲜区 | 000B0014882E | 100543 | Generating | Update Display | 24-07-23 16:16:28 | -- | -- | -- | |

7.2.2 Details of communication record

Click the Details button to view the details of this log.

The screenshot displays the 'Digital Signage Communication Log' interface. The main table lists communication records with columns for Store Number, Area, Device ID, Round Goods, Video Send Status, Task Type, Creation Time, Download Time, Verify Time, Confirm Time (seconds), and Operate. A red box highlights the 'Operate' column for the first row. A 'Log content' popup window is open, showing detailed information for a specific log entry, including Device Information, Task Information, Resource Information, and Layout Information.

| Store Number | Area | Device ID | Round Goods | Video Send Status | Task Type | Creation Time | Download Time | Verify Time | Confirm Time (seconds) | Operate |
|--------------|------|--------------|---------------------|-------------------|----------------|-------------------|-------------------|-------------------|------------------------|---------|
| 0001 | 生鲜区 | 00080014882E | 100543, 100, 100002 | Build Success | Update Display | 24-07-24 10:03:55 | 24-07-24 10:05:04 | 24-07-24 10:05:04 | 1min9s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 18:05:41 | 24-07-23 18:05:26 | 24-07-23 18:05:27 | 45s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 18:05:41 | 24-07-23 18:05:26 | 24-07-23 18:05:27 | 45s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 17:57:30 | 24-07-23 17:58:36 | 24-07-23 17:58:37 | 59s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 17:57:30 | 24-07-23 17:58:36 | 24-07-23 17:58:36 | 58s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 17:49:21 | 24-07-23 17:50:48 | 24-07-23 17:50:48 | 1min27s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 17:24:25 | 24-07-23 17:25:31 | 24-07-23 17:25:33 | 1min7s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 17:24:25 | 24-07-23 17:25:31 | 24-07-23 17:25:34 | 1min8s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 17:12:55 | 24-07-23 17:12:56 | 24-07-23 17:12:56 | 1s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 16:27:46 | 24-07-23 16:28:48 | 24-07-23 16:28:48 | 1min2s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 16:27:46 | 24-07-23 16:28:48 | 24-07-23 16:28:48 | 1min2s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 16:25:41 | 24-07-23 16:27:13 | 24-07-23 16:27:14 | 1min32s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 16:25:41 | 24-07-23 16:27:13 | 24-07-23 16:27:14 | 1min32s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 16:17:20 | 24-07-23 16:19:24 | 24-07-23 16:19:25 | 2min4s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 16:17:20 | 24-07-23 16:19:24 | 24-07-23 16:19:25 | 2min4s | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Generating | Update Display | 24-07-23 16:16:28 | -- | -- | -- | |
| 0001 | 生鲜区 | 00080014882E | 100543 | Build Success | Update Display | 24-07-23 16:16:28 | -- | -- | -- | |

Log content

Device information

Device ID: 00080014882E Store Number: 0001

Task information

Task Type: Update Display

Task ID: 2b1a2416-91ad-423c-8aa7-d15fa553a234

Task status: Build Success Task ending time: 2024-07-24 10:03:55

First download time: 2024-07-24 10:05:04 First confirmation time: 2024-07-24 10:05:04

Resource information

Resource name: 24937080c047289a2a1cd3702f918.png

Download link: http://192.168.4.23:3001/api/download/24937080c047289a2a1cd3702f918.png?taskId=2b1a2416-91ad-423c-8aa7-d15fa553a234&file=00080014882E

Local path: http://192.168.4.23:3001/api/download?taskId=24937080c047289a2a1cd3702f918.png&apicode=0001

Layout information

Grouping: 0 Sort: 0

Left-top vertex-coordinate: 0 Left-top vertex-coordinate: 0

Width: 889 Height: 1280

7.3 Data Synchronization Record

You can quickly find the synchronization records you need, by shop and when the records took place


The screenshot displays the 'Data Synchronization Log' interface. The search filters are highlighted with a red box, showing 'test(0001)' for the store, and 'Start Time' and 'End Time' for the time range. The table below lists synchronization records with columns for Store Number, Log encoding, Log level, Describe, and Time of occurrence.

| Store Number | Log encoding | Log level | Describe | Time of occurrence |
|--------------|--------------|-----------|---|--------------------|
| 0001 | 4002 | info | Data sync done_Find:6014,Update:0,insert:0,SyncType:0-0 | 24-07-23 18:10:55 |
| 0001 | 4002 | info | Data sync done_Find:6014,Update:0,insert:0,SyncType:0-0 | 24-07-23 18:09:52 |
| 0001 | 4002 | info | Data sync done_Find:6014,Update:0,insert:0,SyncType:0-0 | 24-07-23 18:08:49 |
| 0001 | 4002 | info | Data sync done_Find:6014,Update:0,insert:0,SyncType:0-0 | 24-07-23 18:07:45 |
| 0001 | 4002 | info | Data sync done_Find:6014,Update:0,insert:0,SyncType:0-0 | 24-07-23 18:06:42 |
| 0001 | 4002 | info | Data sync done_Find:6014,Update:0,insert:0,SyncType:0-0 | 24-07-23 18:05:40 |
| Global | 4000 | info | DataSync service start,DataSync Server version [3.1.22.0] TaskProducer: '0',DataSyncStatus: '0' | 24-07-23 18:04:37 |
| Global | 4000 | info | DataSync service start,DataSync Server version [3.1.22.0] TaskProducer: '0',DataSyncStatus: '0' | 24-07-23 18:03:55 |

7.4 System Log Query

7.4.1 Query log


You can quickly search for the log information you need, based on shop, message code, log level, and when a log occurs.




The screenshot shows the 'System Log Query' interface. At the top, there is a search bar with fields for 'Please select a store', 'Message code', 'Log Level', 'Start Time', and 'End Time', followed by a 'Search' button. Below the search bar is a table with the following columns: 'Store Number', 'Log encoding', 'Log level', 'System log', 'Time of occurrence', and 'Operate'. The table contains several rows of log entries, all with a log level of 'Error' and a message code of '9999'. The 'System log' column contains detailed error messages, such as 'Unknown error, System.Net.Http.HttpRequestException: Response status code does not indicate success: 401 (Unauthorized), at System.Net.Http.HttpResponseMessage.EnsureSuccessStatusCode() at Titan.Cloud.Service.ResSync.SyncHelper.Post(T1, T2)@HttpClient httpClient,'.

7.4.2 Log details

You can view the details of the log, by clicking the log corresponding to the details button



This screenshot is similar to the previous one, but with a red box highlighting the 'Operate' column for one of the log entries. The 'Operate' column contains a magnifying glass icon, which is the button used to view the details of the log.




This screenshot shows the 'System Log Query' interface with a modal window open. The modal window is titled 'System content' and displays the full text of the log entry selected in the previous screenshot. The log entry text is: 'Unknown error, System.Net.Http.HttpRequestException: Response status code does not indicate success: 401 (Unauthorized), at System.Net.Http.HttpResponseMessage.EnsureSuccessStatusCode() at Titan.Cloud.Service.ResSync.SyncHelper.Post(T1, T2)@HttpClient httpClient,'.

8 Template Management

8.1 ESL Template


8.1.1 Enquiry Template

You can quickly retrieve the ESL templates you need, based on shop, template name, price tag type





8.1.2 Add Template

You can go to the eDesigner for template design, see the eDesigner manual for details.




8.1.3 Import Template

Click on the Import button to select a specific shop to import the template file.




8.1.4 Edit Template

Click on the Edit button to go to the eDesigner to edit the content of this template.




8.1.5 Delete Template

Click the Delete button to delete the specified template.




8.1.6 Download Template

Click the Download button to download the JSON file for the specified template.




8.1.7 Online Template

Online template list can retrieve the required templates by template name, and price tag type for single or batch download.




Click on the download list to see the progress of the download.



8.2 DSL Template


8.2.1 Enquiry Template

DSL templates need to be searched quickly, based on shop, template name, and price tag type.





8.2.2 Add Template

Click the Add button to go to eDesigner for template design, see the eDesigner manual for details.




8.2.3 Import Template

Click on the Import button to select a specific shop to import the template file.




8.2.4 Edit Template

Click the Edit button to go to eDesigner and edit the content of this template.




8.2.5 Delete Template

Click the Delete button to delete the specified template.




8.2.6 Download Template

Click the Download button to download the JSON file for the specified template.



8.2.7 Online Template

You can search the templates you need by template name and price tag type for single or batch downloads.



Click on the download list to see the progress of the download.

The screenshot shows the 'Template Management' interface. On the left, there is a sidebar with navigation options. The main area displays 'Local Template' and 'Online Template' tabs. A search bar and several buttons ('Select All on Page', '+ Download', '+ Download All', and 'Download List') are visible. The 'Download List' panel is open on the right, showing a table with columns: File, Status, Download Time, and Operate. The 'Status' column has two entries: 'Downloading' and 'Download Completed', both highlighted with red boxes. Below the table, it says 'No Data'.

8.3 Template theme



8.3.1 Query theme

You can quickly search for the theme you need, according to the shop, template theme.

The screenshot shows the 'Theme Management' interface. A search bar at the top contains the text 'test[001]' and a 'Search' button. Below the search bar, there is a grid of 16 theme preview cards. Each card displays a different theme design, such as '希望' (Hope), '女神节快乐' (Happy Women's Day), and '开工大吉' (Auspicious Start). The cards are arranged in two rows of eight. At the bottom, there is a pagination control showing 'Total 54' and '16/page'.

8.3.2 Add theme



Click the Add button to add a theme image to the specified shop, you need to enter the theme name and theme size information (for matching different screen sizes). A theme with the same name will be automatically matched for background display during the set shop holidays.



8.4 Holiday Management

8.4.1 Add Holiday

Shop holiday information can be created by clicking on the holiday start time and end time in the calendar and clicking on the Add button.



8.4.2 Delete Holiday

You can delete holiday information by clicking the Delete button for an existing holiday in the calendar.

The screenshot shows the 'Holiday Management' page for July 2024. The calendar displays several holidays. A modal window is open for the holiday '妇女节-红色背景' (Women's Day - Red Background) on July 3rd. The modal includes details such as Store Number: 0001, Start Time: 2024-07-03 09:45, and End Time: 2024-07-03 09:53. A red box highlights the delete button (X) in the top right corner of the modal. Other holidays listed include 'Party Day', '商务风背景', '红色中国风中秋祝福圆月 (1)', and '重阳节 (1)'.

9 System Management

9.1 User Management

9.1.1 Enquiry User



You can quickly retrieve the required user information based on user name, user status, and user role.

The screenshot shows the 'User Management' page. At the top, there is a search form with three input fields: 'Username', 'User status', and 'User role', followed by a 'Search' button. Below the search form is an 'Add' button. The main content is a table with the following columns: Username, Store, Status, Role, Last login time, Contact email, and Operate. The table contains three rows of user data.

| Username | Store | Status | Role | Last login time | Contact email | Operate |
|----------|-------|--------|-------------|-------------------|---------------|---------------------------|
| wdm | 0001 | Normal | admin | 24-07-23 13:14:19 | | [Edit] [Delete] [Refresh] |
| yy | 0001 | Normal | admin | 24-07-24 09:22:05 | | [Edit] [Delete] [Refresh] |
| A | 0001 | Normal | ESL_LCDUser | 24-07-11 16:44:08 | | [Edit] [Delete] [Refresh] |

9.1.2 Add User










You can add a system user by clicking the Add button and entering the user's basic information.



9.1.3 Edit user

You can edit the information of a user by clicking the Edit button corresponding to that user.










The screenshot shows the 'User Management' page in a dashboard. The breadcrumb trail is 'Dashboard / System Management / User Management'. There is a search bar with filters for 'Username', 'User status', and 'User role'. Below the search bar is a '+ Add' button and a table of users. The table has columns for Username, Store, Status, Role, Last login time, Contact email, and Operate. The 'Operate' column contains three icons: a blue edit icon, a red delete icon, and a yellow refresh icon. The edit icon for the user 'wdm' is highlighted with a red box.

| Username | Store | Status | Role | Last login time | Contact email | Operate |
|----------|-------|--------|-------------|-------------------|---------------|---|
| wdm | 0001 | Normal | admin | 24-07-23 13:14:19 | |    |
| yy | 0001 | Normal | admin | 24-07-24 09:22:05 | |    |
| A | 0001 | Normal | ESL_LCDUser | 24-07-11 16:44:08 | |    |

9.1.4 Delete user


You can delete the user information by clicking the Delete button corresponding to the user, and the user will not be able to log in to the system after the deletion.

The screenshot shows the 'User Management' page in a dashboard. The breadcrumb trail is 'Dashboard / System Management / User Management'. There is a search bar with filters for 'Username', 'User status', and 'User role'. Below the search bar is a '+ Add' button and a table of users. The table has columns for Username, Store, Status, Role, Last login time, Contact email, and Operate. The 'Operate' column contains three icons: a blue edit icon, a red delete icon, and a yellow refresh icon. The delete icon for the user 'wdm' is highlighted with a red box.

| Username | Store | Status | Role | Last login time | Contact email | Operate |
|----------|-------|--------|-------------|-------------------|---------------|---|
| wdm | 0001 | Normal | admin | 24-07-23 13:14:19 | |    |
| yy | 0001 | Normal | admin | 24-07-24 09:22:05 | |    |
| A | 0001 | Normal | ESL_LCDUser | 24-07-11 16:44:08 | |    |


9.1.5 Reset Password

Click the Reset Password button for a user to reset the login password for that user.



The screenshot shows the 'User Management' page in a web application. The page has a dark sidebar on the left with various menu items. The main content area displays a table of users. The table has columns for Username, Store, Status, Role, Last login time, Contact email, and Operate. The user 'wdm' is highlighted, and the 'Reset Password' button in the 'Operate' column is circled in red.

| Username | Store | Status | Role | Last login time | Contact email | Operate |
|----------|-------|--------|-------------|-------------------|---------------|--|
| wdm | 0001 | Normal | admin | 24-07-23 13:14:19 | | Edit Delete Reset Password |
| yy | 0001 | Normal | admin | 24-07-24 09:22:05 | | Edit Delete Reset Password |
| A | 0001 | Normal | ESL_LCDUser | 24-07-11 16:44:08 | | Edit Delete Reset Password |



The screenshot shows the 'User Management' page with a 'Reset Password' dialog box open. The dialog box has a title bar with a close button. It contains a 'Username' field with the value 'wdm' and a 'New password' field with a red asterisk indicating it is required. There are 'Cancel' and 'Confirm' buttons at the bottom of the dialog box.

9.2 Rights Management

Click on the Edit Permissions button to view and edit the app permissions for the role.

Dashboard / System Management / Permission Settings

| Role | Status | Audit permission | Remarks | Last Update Time | Operate |
|-----------------|--------|------------------|--------------------|-------------------|------------------|
| admin | Normal | Open | Administrator | 22-05-06 15:24:37 | Edit Permissions |
| manager | Normal | Open | Store manager | 22-05-06 15:24:37 | Edit Permissions |
| pda | Normal | Closure | PDA user,Shop user | 22-05-06 15:24:37 | Edit Permissions |
| advertiser | Normal | Closure | Advertisers | 22-05-06 15:24:37 | Edit Permissions |
| OPEN_API | Normal | Closure | Open api user | 22-05-06 15:24:37 | Edit Permissions |
| ESLUser | Normal | Closure | Est user | 22-05-06 15:24:37 | Edit Permissions |
| LCDUser | Normal | Closure | Lcd user | 22-05-06 15:24:37 | Edit Permissions |
| ADVUser | Normal | Closure | Adv user | 22-05-06 15:24:37 | Edit Permissions |
| ESL_ADVUser | Normal | Closure | Est and adv user | 22-05-06 15:24:37 | Edit Permissions |
| ESL_LCDUser | Normal | Closure | Est and lcd user | 22-05-06 15:24:37 | Edit Permissions |
| LCD_ADVUser | Normal | Closure | Lcd and Adv user | 22-05-06 15:24:37 | Edit Permissions |
| ESL_LCD_ADVUser | Normal | Closure | Est,lcd,adv user | 22-05-06 15:24:37 | Edit Permissions |

Dashboard / System Management / Permission Settings

| Role | Status | Audit permission | Remarks | Last Update Time | Operate |
|-------------|--------|------------------|--------------------|-------------------|------------------|
| admin | Normal | Open | Administrator | 22-05-06 15:24:37 | Edit Permissions |
| manager | Normal | Open | Store manager | 22-05-06 15:24:37 | Edit Permissions |
| pda | Normal | Closure | PDA user,Shop user | 22-05-06 15:24:37 | Edit Permissions |
| advertiser | Normal | Closure | Advertisers | 22-05-06 15:24:37 | Edit Permissions |
| OPEN_API | Normal | Closure | Open api user | 22-05-06 15:24:37 | Edit Permissions |
| ESLUser | Normal | Closure | Est user | 22-05-06 15:24:37 | Edit Permissions |
| LCDUser | Normal | Closure | Lcd user | 22-05-06 15:24:37 | Edit Permissions |
| ADVUser | Normal | Closure | Adv user | 22-05-06 15:24:37 | Edit Permissions |
| ESL_ADVUser | Normal | Closure | Est and adv user | 22-05-06 15:24:37 | Edit Permissions |
| ESL_LCDUser | Normal | Closure | Est and lcd user | 22-05-06 15:24:37 | Edit Permissions |
| LCD_ADVUser | Normal | Closure | Lcd and Adv user | 22-05-06 15:24:37 | Edit Permissions |

Role management

- ESL Electronic Price Tag
- LCD Electronic Price Tag
- LCD Screen
- Product Management
- Shelf
- Settings

→ Add


← Remove

- ESL Electronic Price Tag
- LCD Electronic Price Tag
- LCD Screen
- Product Management
- Shelf
- Settings

9.3 Organizational Structure


9.3.1 Add Organization

To add a subordinate organization, you can click on the Add button of the parent organization.




9.3.2 Edit Organization

You can modify the name of the organization by clicking on the Edit button corresponding to the organization.




9.3.3 Delete Organization

The organization can be deleted by clicking the Delete button for the corresponding organization (deletion is not possible when a subordinate organization exists).



9.4 Parameter setting

After selecting a shop, click the Add button and enter the shop's system configuration information, TFT configuration information, and system feedback configuration information, and click the Save button to save the shop configuration data.



9.5 Administrator Tools

The screenshot shows the Administrator Tools dashboard. On the left is a dark sidebar menu with options: Home, Store Management, Data Management, Data Query, Template Management, System Management, User Management, Permission Settings, Organization Structure, Parameter Settings, and Admin Tools. The main content area has a breadcrumb trail: Dashboard / System Management / Admin Tools. At the top right, there is a dropdown menu 'Please select a store' and icons for mobile, globe, and user. The dashboard features three main cards: 'Enter configuration system' (System Configuration), 'Sync service is not running' (Reload All), and 'Caching service is running' (Reload All). Below these are three form panels: 'TFT screen refresh' with fields for Store, Select area, and Template name; 'ESL refresh' with fields for Store and Template name; and 'OTA Upgrade' with fields for Store number, Select area, Version, Tag MAC address, and Upload OTA file. Red 'Submit' buttons are present in each form panel.

1. Click Configure System to enter the System Configuration page, where you can configure basic system information.


[Shop Configuration](#) -> [Data Sync Configuration](#) -> [Dynamic Model Configuration](#) -> [Model Parameter Configuration](#) -> [Template Configuration](#)

The screenshot shows the 'Shop Configuration' page. It has a breadcrumb trail: Shop Configuration -> Data Sync Configuration -> Dynamic Model Configuration -> Model Parameter Configuration -> Template Configuration. The page contains several form fields: 'Store Number' (Global), 'Data Sync' (Open/Closure), '* Sync Interval' (60), and '* Template Type' (REG,SAL). At the bottom, there are two buttons: 'Next' and 'Restore from Backup System'.


2. The Synchronization Service is restarted.

This screenshot is similar to the first one but highlights the 'Sync service is not running' card with a red box. The 'Sync service is not running' card has a 'Reload All' button. The other cards and form panels remain the same as in the previous screenshot.


3. Cache service restart.




4. Refresh the specified color screen.



5. Refresh the specified price tag.




6. Ota upgrades specified color screen.



9.6 System Configuration

9.6.1 System parameter

You can set the instance name, client code, system language, and current site IP.



9.6.2 Base Station Configuration Parameter

Base station version: 4+ for AP05 base station, base station port: default 9071, after modification, you need to restart the service to take effect, number of attempts: price tag sending failures will enter the blacklist after reaching the number, price tag auto-registration: when you receive a price tag heartbeat after turning on the price tag, it will automatically switch the price tag to the current shop.

9.6.3 Message stack

SMART TAG LEADER

System message notification configuration is possible.

| Message code | Message description | Email | API | Monitor | Operate | |
|--------------|---------------------|-------------------------------------|--------------------------|--------------------------|--------------------------|--------------------------|
| 1029 | AP offline | <input checked="" type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> |
| 2081 | service offline | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> | <input type="checkbox"/> |

9.7 System Font Management

Add the Upload Fonts button to select the fonts that users need to upload to the server. Windows systems require the server to install the fonts manually, and Linux requires a restart of the container after uploading the fonts.

The screenshot displays the 'System Font Management' interface. The left sidebar contains navigation options: Home, Store Management, Data Management, Data Query, Template Management, System Management, User Management, Permission Settings, Organization Structure, Parameter Settings, Admin Tools, and System Configuration. The main content area shows a table of fonts with columns for 'Font name' and 'File name'. The 'Upload Font' button is highlighted with a red box. A modal dialog titled 'Upload Font' is open, featuring a file selection input, instructions for Windows and Linux systems, and 'Cancel' and 'Confirm' buttons.

| Font name | File name |
|---------------|---------------|
| Arial | Arial |
| Bahnschrift | Bahnschrift |
| Calibri | Calibri |
| Cambria | Cambria |
| Cambria Math | Cambria Math |
| Candara | Candara |
| Comic Sans MS | Comic Sans MS |
| Consolas | Consolas |
| Constantia | Constantia |
| Corbel | Corbel |
| Courier New | Courier New |
| Ebrima | Ebrima |

Upload Font

Select font file(ttflttc)

Select font file

For Windows system, please manually install the fonts on the server


After uploading the font on Linux, you need to restart the container for it to take effect

Cancel Confirm

9.8 Application Management

9.8.1 Search App

You can search for the application you want to query by application name.




The screenshot shows the 'Application Management' page in a web application. A search bar is highlighted with a red box, containing the text 'Application name' and a 'Search' button. Below the search bar is a table with the following data:

| APPID | Application name | Version Number | Build number | Describe | Last release time | Download | Operate |
|--------------------------------------|------------------|----------------|--------------|------------|-------------------|------------|---------|
| 5D460546C356CAE04E88-D6FAFBE81A59 | ESL | 3.2.98 | 98 | ESL APP | 24-07-04 19:09:40 | Download ▾ | ⬆️ |
| 4b9fcea8-1dd5-45c8-90d8-6f0937354260 | ePlayer | 3.1.52 | 52 | ADV Player | 24-07-18 18:47:06 | Download ▾ | ⬆️ |
| APDTA546C356CAE04E88-D6FAFBE89998 | AP | 1.0.7.23 | 23 | AP Station | 24-07-08 15:52:20 | Download ▾ | ⬆️ |

9.8.2 Download App


Click on the download button to download the required application files.






The screenshot shows the same 'Application Management' page as above, but with the 'Download' button for the first application (ESL) highlighted with a red box. The table data is identical to the previous screenshot.


9.8.3 Publish App

You can upload a new version of the application file and publish it by clicking the Publish button corresponding to the application.



The screenshot shows the 'Application Management' dashboard. A table lists applications with columns for APPID, Application name, Version Number, Build number, Describe, Last release time, Download, and Operate. The 'Operate' column for the first application (ESL) has a 'Publish' button highlighted with a red box.

| APPID | Application name | Version Number | Build number | Describe | Last release time | Download | Operate |
|--------------------------------------|------------------|----------------|--------------|------------|-------------------|------------|---|
| 5D460546C356CAE04E88-D6FAFBE81A59 | ESL | 3.2.98 | 98 | ESL APP | 24-07-04 19:09:40 | Download ↘ |  |
| 4b9fcea8-1dd5-45c8-90d8-6f0937354260 | ePlayer | 3.1.52 | 52 | ADV Player | 24-07-18 18:47:06 | Download ↘ |  |
| APOTA546C356CAE04E88-D6FAFBE89998 | AP | 1.0.723 | 23 | AP Station | 24-07-08 15:52:20 | Download ↘ |  |



The screenshot shows the 'Publish New Version' dialog box. The dialog has the following fields and buttons:

- Application name: ESL
- Build number: 98
- Version Number: 3.2.98
- Upload files: Select installation file
- Buttons: Cancel, Confirm