

## **Overview**

The Tracer LPLI series MPPT solar charge controller combines solar charge controller and LED constant current driver into one unit which is ideal for solar LED Lighting, especially when dimmer function is needed. The advanced Maximum Power Point Tracking charging methods enables the system charging and discharging management to obtain the most radical optimization. Increase the system flexibility, yet lower down the system cost.



## **Features**

- Advanced Maximum Power Point Tracking (MPPT) technology, with tracking efficiency no less than 99.5%
- Maximum conversion efficiency of 98%
- Accurately recognizing and tracking of multiple power points
- Ultra-fast tracking speed and guaranteed tracking efficiency
- Adopt high quality components of ST,IR and Infineon, make sure product using lifespan
- Apply to lead-acid battery and lithium battery
- Lithium battery self-activating function
- Lithium battery low temperature protection function
- Charging current limit, with settable current
- Lithium battery limit current in low temperature
- Intelligent power mode with 365-day lighting control technology
- Load reduce power automatically
- Digital precision constant current control and the control accuracy are less than ±2%
- Maximum output efficiency of 96%
- PV and Load power limitation function
- The output current can be adjusted among the rated power and current range
- Real-time energy statistics function
- Monitoring and setting parameter via Mobile APP and RC10 with IR function
- Aluminum housing for better cooling
- Wide working environment temperature(-40℃ ~ 60℃)
- IP68 waterproof degree
- Long lifespan design, five years warranty

## **Electronic protections**

- PV Reverse Polarity
- Battery Reverse Polarity
- Battery Over Voltage
- Battery Over Discharge
- Battery Overheating
- Lithium battery Low Temperature (Default 35°C)
- Lithium battery limit current in low temperature













## **Technical Specifications**

| Мо                              | del                               | Tracer1305<br>LPLI  | Tracer2606<br>LPLI  | Tracer3906<br>LPLI                      | Tracer5206<br>LPLI          | Tracer2610<br>LPLI   | Tracer3910<br>LPLI   | Tracer5210<br>LPLI   |  |  |  |
|---------------------------------|-----------------------------------|---|---|---|-----------------------------|--|----------------------|----------------------|--|--|--|
| Nominal system voltage          |                                   | 12VDC   | 12/24VDC  |   |                             |  |                      |                      |  |  |  |
| Battery input voltage range     |                                   | 8.5 ~ 16VDC   | 8.5 ~ 32VDC   |   |                             |  |                      |                      |  |  |  |
| Rated charge current ★          |                                   | 10A/12V   | 10A   | 15A                                     | 20A                         | 10A  | 15A                  | 20A                  |  |  |  |
| Rated charge power              |                                   | 130W/12V  | 130W/12V<br>260W/24V  | 195W/12V<br>390W/24V                    | 260W/12V<br>520W/24V        | 130W/12V<br>260W/24V   | 195W/12V<br>390W/24V | 260W/12V<br>520W/24V |  |  |  |
| Max. PV open circuit voltage    |                                   | 48V(Min. Temp.)<br>45V(25°C)  |   | operating environm<br>℃ environment ten |                             | 95V(at minimum operating environment temperature)<br>92V(at 25℃ environment temperature) |                      |                      |  |  |  |
| MPP Voltage range               |                                   |   | ( Battery volta   | ge+2V) ~ 36V                            | ( Battery voltage+2V) ∼ 72V |  |                      |                      |  |  |  |
| Max. output current             |                                   | 3.3A  | 3.3A  | 4.5A                                    | 6.6A                        | 3.3A   | 4.5A                 | 6.6A                 |  |  |  |
| Max. output power               |                                   | 100W  | 100W  | 130W                                    | 200W                        | 100W   | 130W                 | 200W                 |  |  |  |
| Output voltage range            |                                   | ( Max. battery voltage+2V) ~ 46V  | ( Max. battery voltage+2V) ~ 58V                              |   |                             | ( Max. battery voltage+2V) ~ 80V   |                      |                      |  |  |  |
| Load open circuit voltage       |                                   | 46V   | 58V   |   |                             | 80V  |                      |                      |  |  |  |
| Load over voltage protection    |                                   | 50V   | 63V   |   |                             | 100V   |                      |                      |  |  |  |
| Maximum output efficiency       |                                   | 96%   |   |   |                             |  |                      |                      |  |  |  |
| Output current control accuracy |                                   | ≤±2%  |   |   |                             |  |                      |                      |  |  |  |
| Battery Type                    |                                   | Lead-acid battery: Sealed(default)/Gel/Flooded/User; Lithium battery:LiFePO4/Li-NiCoMn/User |   |   |                             |  |                      |                      |  |  |  |
| Lead-acid                       | Equalization Voltage              | Sealed:14.6V; Flooded:14.8V;User:9-17V (24Vsystem×2)  |   |   |                             |  |                      |                      |  |  |  |
|                                 | Boost Voltage                     | Sealed:14.4V;Gel:14.2V;Flooded:14.6V;User:9-17V(24Vsystem×2)                                |   |   |                             |  |                      |                      |  |  |  |
|                                 | Float Voltage                     | Sealed/Gel/Flooded:13.8V;User:9-17V(24Vsystem×2)  |   |   |                             |  |                      |                      |  |  |  |
|                                 | Low Voltage<br>Reconnect Voltage  | Sealed/Gel/Flooded:12.6V;User:9-17V(24Vsystem×2)  |   |   |                             |  |                      |                      |  |  |  |
|                                 | Low Voltage<br>Disconnect Voltage | Sealed/Gel/Flooded:11.1V;User:9-17V(24Vsystem×2)  |   |   |                             |  |                      |                      |  |  |  |
| Lithium                         | Boost Charging Voltage            | LiFePO4(4s):14.5V/Li-NiCoMn(3s):12.5V/User:9-17V(24Vsystem×2)                               |   |   |                             |  |                      |                      |  |  |  |
|                                 | Low Voltage<br>Reconnect Voltage  |   | LiFePO4(4s):12.8V/Li-NiCoMn(3s):10.5V/User:9-17V(24Vsystem×2) |   |                             |  |                      |                      |  |  |  |
|                                 | Low Voltage<br>Disconnect Voltage |   | LiFePO4(4s):11.1V/Li-NiCoMn(3s):9.3V/User:9-17V(24Vsystem×2)  |   |                             |  |                      |                      |  |  |  |

| Self-consumption                    | ≤15mA/12V;≤22mA/24V  |        |               |  |  |               |  |  |  |  |
|-------------------------------------|--|--------|---------------|--|--|---------------|--|--|--|--|
| Communication                       | IR communication   |        |               |  |  |               |  |  |  |  |
| Working environment Tem.            | -40 ℃ ~ +60 ℃  |        |               |  |  |               |  |  |  |  |
| Enclosure                           | IP68(1.5m,72h)   |        |               |  |  |               |  |  |  |  |
| Overall dimension ( mm )            | 124×8  | 9×30   | 150×93.5×32.7 | 153×105×52.1   | 124×89×30  | 150×93.5×32.7 | 153×105×52.1   |  |  |  |
| Mounting hole size ( mm )           | Ф3.5mm   |        |               |  |  |               |  |  |  |  |
| Mounting dimension ( mm )           | 88×76mm  |        | 120×83mm      | 120×94mm   | 88×76mm  | 120×83mm      | 120×94mm   |  |  |  |
| Power cable ( AWG/mm <sup>2</sup> ) | PV/BAT:14AWG(2.5mm <sup>2</sup> )<br>LOAD:18AWG(1.0mm <sup>2</sup> ) |        |               | PV/BAT:12AWG<br>(4mm <sup>2</sup> )<br>LOAD:16AWG<br>(1.5mm <sup>2</sup> ) | PV/BAT:14AWG(2.5mm <sup>2</sup> )<br>LOAD:18AWG(1.0mm <sup>2</sup> ) |               | PV/BAT:12AWG<br>(4mm <sup>2</sup> )<br>LOAD:16AWG<br>(1.5mm <sup>2</sup> ) |  |  |  |
| Net weight                          | 0.52kg   | 0.52kg | 0.71kg        | 1.18kg   | 0.52kg   | 0.71kg        | 1.18kg   |  |  |  |

<sup>★</sup>The controller has the limit charge current function, the current can be set via the APP software and RC10.